# SOLID ELECTROLYTE OXYGEN REGENERATION SYSTEM

# INTERIM REPORT

by

J.W. Shumar, G. G. See, F. H. Schubert and J. D. Powell

# **July, 1976**

(NASA-CE-137813) SOLID ELECTROLYTE OXYGEN REGENERATION SYSTEM Interim Peport, 26 Sep. 1973 - 31 Mar. 1976 (Life Systems, Inc., Cleveland, Ohio.) 201 p HC (CSCL 06K)

N76-30815

Unclas G3/54 50504

Prepared Under Contract No. NAS2-7862

by

Life Systems, Jnc. Cleveland, Ohio 44122

SEP 1976
RECEIVED
NASA STI BACILITY
INPUT BRANCH

for

# **AMES RESEARCH CENTER**

National Aeronautics and Space Administration Moffett Field, California 94035

ER-190-12

# SOLID ELECTROLYTE OXYGEN REGENERATION SYSTEM

INTERIM REPORT

by

J. W. Shumar, G. G. See, F. H. Schubert and J. D. Powell

July, 1976

Distribution of this report is provided in the interest of information exchange. Responsibility for the contents resides in the authors or organization that prepared it.

Prepared Under Contract No. NAS2-7862

by

LIFE SYSTEMS, INC. Cleveland, Ohio 44122

for

AMES RESEARCH CENTER

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

*	

# FOREWORD

The development described in this report was performed by Life Systems, Inc. under NASA Contract NAS2-7862. The work was performed during the period beginning September 26, 1973 through March 31, 1976. The Program Manager was J. W. Shumar. Technical support was provided as follows:

Personnel	Area(s) of Responsibility
Gary G. See	Mechanical design
J. David Powell	Electrical design
Franz H. Schubert	Mechanical and system design
Glenn A. Little	Ground Support Accessories layout and fabrication, and component testing
Rick A. Wynveen, PhD	Program administration, electrochemical support
Kamal K. Kacholia	Chemical engineering support

The contract's Technical Monitor was P. D. Quattrone, Chief, Environmental Control Research Branch, NASA Ames Research Center, Moffett Field, CA with assistance from Layton Ingelfinger, NASA Ames Research Center.

The solid electrolyte oxygen regeneration concept was based upon the work performed by Applied Electrochemistry, Inc., Sunnyvale, CA, in designing, developing, fabricating and delivering the solid electrolyte cells for incorporation into the Solid Electrolyte Oxygen Regeneration System. This work was conducted under NASA Contracts NAS2-4843 and NAS2-6412.

# TABLE OF CONTENTS

																																	PAGE
LIST	OF I	FIGU	RES	•	•	•	•	•		•	•	•	•	•	•	•		•		•	•	•		•	•	•	•	•	•	•	•		iii
LIST	OF 7	ΓAΒL	ES	•		•	•	•	•	•		•	•		•	•	•	•	•			•	•	•	•	•	•	•	•	•	•	•	iv
SUMMA	ARY .			•	•	•	•		•	•	•				•	•	•		•	•	•	•	•	•	•	•	•	•	•	•	•	•	1
INTRO	ODUC"	rion		•		•	•	•		•	•	•	•			•	•	•			•	•		•	•	•	•			•	•	•	2
	Bacl Syst Prog	tem	Des	cri	ipt	ic	n						•		•			•							•			•	•	•	•		3 4 4
SX-1	SYS	ГЕМ	DES	IGN	1		•	•	•	•	•			•		•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	6
	Syst Syst Syst	tem	Cap	aci	iti	ies	5				•					•	•							•			•		•			•	6 7 7
		Ca CC Ni Ga	ter rbo Di tro s E	n I spi ger xit	Dic rop n F	oxi oor our ar	ide ti ge id	on Sa	ele nat	ct or ole	ro H	01) Fee	/zed	er Ga •	ar as	nd Fi •	Re 11	ecy ·	c1	.e		• •	•	•	•	•		•	•		•	•	7 11 12 12 13 14
	Syst	tem	0pe	rat	ir	ng	Mc	od€	s	•	•	•	•	•	•			•	•	•	•	•	•	•	•	•	•	•	•	•	•		14
		St No Pu	utd and rma rge rbo	by 1 M	Mod Mod	ode le	•	:	:			•	•	•	•	•		•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	14 14 15 15
SYSTI	EM H	ARDW	ARE	DI	ESC	CR	[P]	CIC	N					•	•	•	•		•	•			•		•	•	•			•		•	15
	Elec	ctro	lyz	er	Sı	ıba	155	en	nb]	ly		•		•		•		•	•	•		•	•	•	•	•	•			•	•	•	18
			ect ect		•								•	•	•	•				•	•			•	•		•	•	•	•	•	•	18 18
CO D	ISPR	OPOF	TIO	NA'	roi	3	•	•		•	•					•	•	•	•	•	•	•	•	•		•	•	•	•	•	•	•	26
н <sub>2</sub> sı	EPAR	ATOF	١.	•	•	•	•	•	•	•		•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	26
WATE	R FE	ED N	1ECH	AN:	ISN	M	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	30

# Table of Contents - continued

<u> </u>	AGE
CONTROL INSTRUMENTATION	30
MONITOR INSTRUMENTATION	41
GROUND SUPPORT ACCESSORIES	57
Ground Checkout Unit	57 57 60 60
PRODUCT ASSURANCE PROGRAM	60
Quality Assurance	62 62 63
System Design Guidelines	
Maintainability	68
PROGRAM TESTING	69
Electrolyzer Drum Leak Tests	69 70 70 74 82
CONCLUSIONS AND RECOMMENDATIONS	91
REFERENCES	93
ADDENDTY 1	44 4

# LIST OF FIGURES

FIGURE		PAGE
1	Solid Electrolyte Oxygen Regeneration System	5
2	SX-1 Schematic	10
3	Front View of Assembled SX-1	16
4	Complete Electrolyzer Furnace Assembly	19
5	Electrolyzer Drum	22
6	Electrolyzer Module	25
7	CO Disproportionator	27
8	H <sub>2</sub> Separator	29
9	Disassembled Hydrogen Separator	31
10	H <sub>2</sub> O Temperature Versus Flash Boiler Tube Length	33
11	Water Feed Mechanism	34
12	SX-1 Allowed Mode Transitions	40
13	Control Instrumentation	42
14	Control Instrumentation Front Panel	44
15	Monitor Instrumentation	45
16	SX-1 Ground Support Accessories	58
17	Ground Checkout Unit Panel	59
18	SX-1 FSU Schematic	61
19	Failure Mode Effects and Criticality Analysis	64
20	CO Disproportionator Conversion Efficiency Versus	
	Temperature	75
21	Water Feed Mechanism Test Stand	80
22	Water Feed Mechanism Flow Rate Versus Time	81
23	CO Disporportionator Temperature Control Characteristics	83
24	Electrolyzer Module Temperature Control Characteristics	84
A1-1	SX-1 Schematic	A1-15

# LIST OF TABLES

TABLE		PAGE
1	System Design Specifications	8
2	CO <sub>2</sub> Collection Subsystem Interfaces	9
3	SX-1 Components List	17
4	SX-1 Electrolyzer Furnace Operating Characteristics and Materials	21
5	Electrolyzer Subassembly Performance Characteristics	24
6	SX-1 Carbon Monoxide Disproportionator and Catalyst Activation Furnace Operating Characteristics and Materials	28
7	SX-1 Hydrogen Separator Operating Characteristics and Materials	32
8	SX-1 Steady State Controlled Parameters	35
9	Control Instrumentation PC Card List	43
10	SX-1 Shutdown Protection	47
11	SX-1 Monitored Parameters	50
12	Monitor Instrumentation Printed Circuit Card List	56
13	Electrolyzer Drum $\Delta t/\Delta P$ Test Results	71
14A	Hydrogen Separator Test Results Summary (Metric Units)	72
14B	Hydrogen Separator Test Results Summary (English Units)	73
15A	CO Disproportionator Test Results (Metric Units)	76
15B	CO Disproportionator Test Results (English Units)	78
16	Monitor Instrumentation Voltage Trip Points	85
17A	Monitor Instrumentation Trip Points (Metric Units)	87
17B	Monitor Instrumentation Trip Points (English Units)	89

#### SUMMARY

A program to design, develop, fabricate and assemble a One-Man, Self-Contained, Solid Electrolyte Oxygen Regeneration System (SX-1) incorporating solid electrolyte electrolyzer drums that were designed, developed, fabricated and tested under Contracts NAS2-2810, NAS2-4843, and NAS2-6412 was completed. SX-1 is a preprototype engineering model designed to produce 0.952 kg (2.1 1b)/day of breathable oxygen (02) from the electrolysis of metabolic carbon dioxide (CO<sub>2</sub>) and water vapor. The CO<sub>2</sub> supply rate was established based on the metabolic CO<sub>2</sub> generation rate for one man of 0.998 kg (2.2 lb)/day. water supply rate (0.254 kg (0.56 lb)/day) was designed to be sufficient to make up the difference between the 0.952 kg (2.1 lb)/day 0, generation specification and the O<sub>2</sub> available through CO<sub>2</sub> electrolysis, 0.726 kg (1.6 lb)/day. The SX-1 was successfully designed, fabricated and assembled. Design Verification Tests (DVT) or the CO Disproportionators, H2 Separators, Control Instrumentation, Monitor Instrumentation, Water Feéd Mechanism were successfully completed. The erratic occurrence of electrolyzer drum leakage prevented the completion of the CO, Electrolyzer Module and Water Electrolyzer Module DVT's and also prevented the performance of SX-1 integrated testing. Further development work is required to improve the solid electrolyte cell high temperature seals.

The SX-1 was designed with electronic Control and Monitor Instrumentation to carry out operating mode change sequences, regulate performance, analyze and display performance trends and detect faults.

Other major components that were designed, fabricated, assembled, tested, and incorporated into the SX-1 include the Carbon Monoxide (CO) Disproportionators in which CO is converted to CO<sub>2</sub> and solid carbon, Hydrogen (H<sub>2</sub>) Separators which remove excess H<sub>2</sub> from the SX-1 feed gas and recycle loop gas, a high temperature Recycle Loop Bellows Pump which provides the recycle loop gas flow, Hot Gas Valves which allow servicing of the CO Disproportionators, and a Water Feed Mechanism which provides the water vapor for the Water Electrolyzer Module at a stable steam flow rate.

The Ground Support Accessories (GSA) required to test the SX-1 were designed, fabricated, assembled and functionally checked out. The GSA were designed to simulate the actual spacecraft interfaces for three candidate CO<sub>2</sub> removal systems: the Electrochemical Depolarized Concentrator (EDC), the Molecular Sieve and the Steam-Desorbed Solid Amine. The GSA consisted of a Fluid Supply Unit (FSU), a Space Vacuum Simulator (SVS), a Gas Products Monitor (GPM), a Ground Checkout Unit (GCU), component checkout stands and a Carbon Deposition Cartridge (CDC) activation facility.

A Product Assurance Program incorporated quality assurance, reliability, maintainability, safety and materials control. Activities included conducting design review meetings, preparing a Failure Mode Effects and Criticality Analysis (FMECA), preparation of safety design criteria, and monitoring of system design and fabrication with regard to quality control maintainability and materials compatibility.

Program testing consisted of performing component checkout tests and major component DVTs.

- The CO Disproportionator was successfully tested for 28 days at operating temperatures ranging from 773 to 843K (932 to 1058F) and at feed gas flow rates from 683 sccm (0.02 scfm) to 3670 sccm (0.13 scfm). The CO Disproportionator conversion efficiency exceeded the design goal of 36%.
- The H<sub>2</sub> Separators were successfully tested at temperatures from 611 to 650K (640 to 711F). The feed gas H<sub>2</sub> Separator exceeded the design H<sub>2</sub> removal rate goal by 67% and the recycle loop H<sub>2</sub> Separator exceeded the design H<sub>2</sub> removal rate goal by 27%.
- The Water Feed Mechanism was successfully tested for 60 hours at its design operating temperature. The Water Feed Mechanism delivered steam in a stable flow mode at feed rates up to 1.8 times the design water vapor feed rate of 0.245 kg (0.54 lb)/day.
- The Control Instrumentation mode transition sequences and control functions were tested. All mode transitions were successfully accomplished and all control functions performed satisfactorily at their design points.
- The Monitor Instrumentation was tested by simulating sensor outputs from the SX-1 and verifying the Monitor Instrumentation setpoints that were set for the individual printed circuit (PC) cards.
- Leak tests were performed on the electrolyzer drums that were produced under NAS2-6412. The results indicated that several of the drums leaked. This erratic occurrence of electrolyzer drum leakage prevented the performance of integrated SX-1 testing.
- Other testing successfully completed included checkout tests on the Hot Gas Valves at their operating conditions, checkout tests on all SX-1 off-the-shelf components including valves, pressure transducers, pressure regulators, thermocouples, thermistors and flow restrictors.

As part of parallel technology activities, the methods for analyzing the SX-1 recycle loop and product gases were established and a computer program for calculating the gas composition at various points in the SX-1 recycle loop was developed.

#### INTRODUCTION

There is a definite need for systems that can recover oxygen  $(0_2)$  from metabolically produced carbon dioxide  $(C0_2)$  for future extended duration manned spaceflights. Such a system could reduce flight weight by eliminating the need for carrying stored  $0_2$  (in the form of water or equivalent) at launch.

Several concepts which partially or completely perform this function have been proposed and studied. Some of these are the Fused Salt concept, the Solid Electrolyte concept, the Bosch Reactor concept, the Sabatier-Methane Dump concept, the Sabatier-Methane Decomposition concept, and the Sabatier-Acetylene Dump concept. The results of the study for evaluating and selecting life support systems for a 500-day non-resupply mission revealed that the most promising route for 0, recovery from CO, was electrolysis using solid oxide electrolyzers and Carbon Monoxide (CO) Disproportionators with replaceable cartridges. Several features of the Solid Electrolyte concept led to its selection. The Solid Electrolyte Oxygen Regeneration System (SEORS) combines the function of two separate subsystems that are required in alternate Oxygen Regeneration Systems (ORS); a CO, Reduction Subsystem such as a Bosch or Sabatier reactor and an Oxygen Géneration Subsystem (water electrolyzer). the solid electrolyte concept, both CO, reduction and water electrolysis are carried out in the solid electrolyte electrolyzer cells. As a result, an ORS based on the solid electrolyte concept has a low equivalent weight, a minimum of interfaces, simplified instrumentation and an absence of condensor separators.

## Background

The concept of 0, ion transfer through solid electrolytes was first investigated by Nernst and Reynolds in the early 1900's. However, it was only recently that the unusual electrical properties of solid electrolytes had been put to practical use. This is generally attributed to the recent development of high temperature materials and sealing techniques which are required for the application of products based upon the solid electrolyte concepts.

Initial work involving the application of solid electrolyte cells for  $0_2$  regeneration was carried out by Chandler and Pollara in the early  $1960^4$ s. They built and operated a system that produced 150 cc/min  $(5.3 \times 10^{-3} \text{ cfm})$   $0_2$ . The life of their system was short and a deterioration in the catalytic activity of their carbon deposition reactor was observed.

More recently Weissbart and Smart, (4) conducted investigations on alternate solid electrolyte materials and also designed, developed, fabricated and tested electrolyzer drums based on a flat plate solid electrolyte configuration. A six-drum, 12-cell, 24-ampere electrolyzer module was operated continuously for over 2,000 hours. The Faradaic current efficiency was 100% and 0<sub>2</sub> produced contained less than 0.4% CO<sub>2</sub> as an impurity. The test program included the integration of the electrolyzer module with a carbon deposition reactor.

Elikan and co-workers, during the same time period, designed, developed, fabricated and tested multicell electrolysis batteries, a carbon deposition reactor and palladium (Pd) foil hydrogen (H<sub>2</sub>) diffusers. The electrolysis batteries of the "bell and spigot" design, as well as the continuous carbon deposition reactor, operated independently for periods exceeding 100 days. (8)

<sup>(1)</sup> Numbers in parentheses are references found at the end of this report.

Subsequent to this work, a 1/4-man SEORS, consisting of an electrolyzer with "bell and spigot" cells, a carbon deposition reactor and Pd H<sub>2</sub> Separator were designed, fabricated and tested. The system was operated for 180 days. However, the O<sub>2</sub> purity decreased with operating time. The major impurity in the O<sub>2</sub> was CO<sub>2</sub> with lesser amounts of water, nitrogen (N<sub>2</sub>) and CO. The SAE Bioenvironmental Systems Advisory Committee, in a study of alternate methods for reclaiming O<sub>2</sub> from CO<sub>2</sub>, attributed the relatively high CO<sub>2</sub> content in the product O<sub>2</sub> to the questionable adequacy of the "bell and spigot" cell sealing techniques.


# System Description

A block diagram which describes the One-Man, Self-Contained, Solid Electrolyte Oxygen Regeneration System (SX-1) operation and depicts the major SX-1 components is shown in Figure 1. The major components are the CO<sub>2</sub> and Water Electrolyzer Modules which convert CO<sub>2</sub> and water into CO and O<sub>2</sub>, and H<sub>2</sub> and O<sub>2</sub>, respectively; the CO Disproportionators in which CO is converted into CO<sub>2</sub> and solid carbon; H<sub>2</sub> Separators which remove excess H<sub>2</sub> from the SX-1 feed gas and recycle loop gas; a high temperature Recycle Loop Bellows Pump which provides the recycle loop gas flow; Hot Gas Valves which allow servicing of the CO Disproportionators, and a Water Feed Mechanism which provides the water vapor for the Water Electrolyzer Module at a stable steam flow rate. The SX-1 also incorporated electronic Control and Monitor Instrumentation to carry out operating mode change sequences, regulate performance, analyze and display performance trends and detect faults.

#### Program Objectives

The objective of this program was to design, develop, fabricate, assemble and test an SX-1, incorporating electrolyzer drums that were designed, developed and fabricated under Contracts NAS2-2810, NAS2-4843 and NAS2-6412. To accomplish the above, the program was divided into five tasks and program management functions. The specific objectives of the five tasks were to:

- 1. Design, develop, fabricate and assemble a one-man, preprototype engineering model of the SX-1. This task included (a) defining the system and its operating modes, (b) designing, fabricating, and assembling CO<sub>2</sub> and Water Electrolyzer Modules, CO Disproportionators, H<sub>2</sub> Separators, Control and Monitor Instrumentation, Hot Gas Valves, valves, regulators and transducers, and (c) designing the system packaging to ensure optimum system performance, maintainability, safety and reliability.
- 2. Design, fabricate, assemble and functionally check out the Ground Support Accessories (GSA) required for performing the parametric and endurance test on the system. The GSA consists of:
  - a. A Fluid Supply Unit (FSU) which contains the valves, flowmeters and pressure regulators required to control the H<sub>2</sub>, CO<sub>2</sub>, water, N<sub>2</sub> and O<sub>2</sub> supplies required to simulate the interface from three CO<sub>2</sub> Collection Systems: The Electrochemical Depolarized Concentrator (EDC), the Steam-Desorbed Solid Amine and the Molecular Sieve



- b. A Space Vacuum Simulator (SVS) which contains the vaccum pumps, pressure gauges and traps required to simulate  $\rm H_2$  venting to space vacuum
- c. A Gas Products Monitor (GPM) which includes  ${\rm H_2}$  and  ${\rm O_2}$  flow, pressure, temperature and purity monitoring provisions
- d. A Ground Checkout Unit (GCU) which consists of meters, switches and displays required to measure system performance in engineering units
- e. A Carbon Deposition Cartridge (CDC) activation facility
- f. Component checkout stands
- 3. Conduct a Product Assurance Program to ensure that the concepts of quality control, maintainability, safety and reliability were incorporated into the design and fabrication of the SX-1.
- 4. Conduct the program testing including component checkouts, calibration and Design Verification Tests (DVT).
- 5. Carry out supporting studies associated with the SX-1 system development. Supporting studies consisted of establishing analytical methods for analyzing the feed gases, the recycle loop gases and product gases.

The following sections summarize the results of the program and the conclusions and recommendations reached.

#### SX-1 SYSTEM DESIGN

## System Function

The function of the SX-1 is to generate 0.952 kg (2.1 lb) of breathable  $0_2/\mathrm{day}$ . This is accomplished by electrolyzing the metabolic  $\mathrm{CO}_2$  produced by one man, 0.998 kg (2.20 lb/day) and water vapor that is available from the spacecraft Water Management System and from water vapor carried by the exhaust of the  $\mathrm{CO}_2$  Collection System. The  $0_2$  obtained from the electrolysis of the metabolic  $^2\mathrm{CO}_2$  is 0.726 kg (1.6 lb/day). To supplement this, 0.254 kg (0.56 lb/day) of water is electrolyzed to yield 0.22 kg (0.5 lb/day) of  $^0\mathrm{CO}_2$ . The net reactions describing the electrolysis of  $\mathrm{CO}_2$  and water are

$$CO_2 = CO + {}^{1}_{2}O_2$$
 (1)

and

$$H_2^0 = H_2 + {}^{1}_{2}0_2 \tag{2}$$

As a result of the CO and  $\rm H_2$  produced in the electrolysis reaction, it is necessary to include a CO Disproportionator and a  $\rm H_2$  Separator in the recycle loop of the SX-1. The function of the CO Disproportionator is to convert CO produced in Reaction 1 to  $\rm CO_2$  and solid carbon. This ensures the maximum recovery of  $\rm O_2$  from the  $\rm CO_2$ . The reaction taking place in the CO Disproportionator is

$$2CO = CO_2 + C$$
 (3)

The solid carbon is collected in replaceable cartridges which are discarded. The function of the H<sub>2</sub> Separator is to remove H<sub>2</sub> from the recycle loop. Hydrogen is introduced into the recycle loop in two ways: (1) it is carried along by the exhaust of the CO<sub>2</sub> Collection System, and (2) it is created in the CO<sub>2</sub> Electrolyzer Modules by electrolysis of water vapor carried along by the feed gases. It is important that the excess H<sub>2</sub> be removed from the recycle loop, otherwise it would accumulate and cause an increase in loop pressure and dilute the volume percentage of CO<sub>2</sub> in the electrolyzer. Eventually the SX-1 would experience a high CO<sub>2</sub> electrolyzer drum voltage shutdown caused by H<sub>2</sub> blanketing the cathode or a high pressure shutdown.

## System Capacities

The capacities and operating characteristics of the SX-1 are described in the system design specifications presented in Table 1. This data is based on the SX-1 interfacing with an EDC CO<sub>2</sub> Collection System. A system block diagram showing components and system interfaces based on interfacing with the EDC CO<sub>2</sub> Collection System was shown in Figure 1. The SX-1 was designed to be capable of operating with the feed gas interfaces from three CO<sub>2</sub> Collection Systems: EDC, Molecular Sieve and Steam-Desorbed Solid Amine. Table 2 lists the interfaces for the three CO<sub>2</sub> Collection Subsystems.

#### System Schematic

The SX-1 system schematic is shown in Figure 2. The major components of the system are an Electrolyzer Subassembly containing a Water Electrolyzer Module and three  ${\rm CO}_2$  Electrolyzer Modules, a Water Feed Mechanism, two CO Disproportionators, Recycle Loop Bellows Pump, two H<sub>2</sub> Separators, four Hot Gas Valves, Control and Monitor Instrumentation, and a N<sub>2</sub> Purge System.

# Water Electrolyzer

Water from the GSA is supplied through the deionizer, DE101, and solenoid valve, SV101, to the Water Feed Mechanism, FB101. The Water Feed Mechanism is a zero gravity design that utilizes a flash orifice and a pre-heater and super-heater section to convert the water to water vapor for entry into the Water Electrolyzer Module. The water vapor is decomposed in the water electrolyzer. The net reaction is

$$H_2^0 = H_2 + \frac{1}{2}O_2 \tag{4}$$

# TABLE 1 SYSTEM DESIGN SPECIFICATIONS (a)

Number of Crew (Continuous)	1
Oxygen Produced, kg/s (Lb/Day) From CO <sub>2</sub> Electrolysis From Water Electrolysis Total	$\begin{array}{c} 8.502 \times 10^{-6} \\ 2.533 \times 10^{-6} \\ \hline 11.035 \times 10^{-6} \end{array} \begin{array}{c} (1.618) \\ (0.482) \\ \hline (2.100) \end{array}$
Oxygen Purity, % CO CO <sup>2</sup>	<0.5 None Detectable
Hydrogen Produced, kg/s (Lb/Day) From Water Electrolyzer Separated from Recycle Loop Separated from Feed Gas Total	$\begin{array}{c} 0.315 \times 10^{-6} & (0.060) \\ 0.074 \times 10^{-6} & (0.014) \\ 0.100 \times 10^{-6} & (0.019) \\ \hline 0.489 \times 10^{-6} & (0.093) \end{array}$
Hydrogen Purity (excluding water vapor), $\% H_2$	>98
Carbon Produced, kg/s (Lb/Day)	$3.158 \times 10^{-6} (0.601)$
Feed Gas Composition, kg/s (Lb/Day) (a)  CO H Water	$11.560 \times 10^{-6} (2.200)$ $0.163 \times 10^{-6} (0.031)$ $0.105 \times 10^{-6} (0.020)$
Water Supply Flow Rate, kg/s (Lb/Day) Pressure, N/m <sup>2</sup> (Psia) Temperature, K (F)	$2.848 \times 10^{-6} (0.542)$ 31.030 x 10 <sup>4</sup> (45) 277.6 to 291.5 (40 to 65)
Nitrogen Purge Supply Pressure, N/m <sup>2</sup> (Psia)	$31.030 \times 10^4 (45)$
Recycle Loop Pressure, N/m <sup>2</sup> (Psia) Flow, m <sup>3</sup> /s (S1pm)	$10.3 \times 10^{4} \text{ to } 11.0 \times 10^{4}$ (15 to 16) $5.1 \times 10^{-5} (3.08)$
Cabin Atmosphere Total Pressure, N/m <sup>2</sup> (Psia)	$10.1 \times 10^4$ to $10.4 \times 10^4$ (14.7 to 15.2)
Temperature, K (F) Dew Point Temperature, K (F) O <sub>2</sub> Partial Pressure, N/m <sup>2</sup> (Psia)	291.5 to 297.0 (65 to 75) 280.9 to 287.0 (46 to 57) 2.1 x 10 <sup>4</sup> to 2.3 x 10 <sup>4</sup> (3.04 to 3.28)
Heat Rejection Sink	Ambient Air
Purge Sink	Vacuum

<sup>(</sup>a) Based on EDC interface.

TABLE 2 CO<sub>2</sub> COLLECTION SUBSYSTEM INTERFACES

	Flow Rate, kg/s	(Lb/Day)	Percent
EDC			
CO <sub>2</sub>	$11.56 \times 10^{-6}$	(2.200)	97.8
H <sub>2</sub>	$0.16 \times 10^{-6}$	(0.031)	1.4
Water	$0.10 \times 10^{-6}$	(0.019)	0.8
Molecular Sieve			
co <sub>2</sub>	$11.56 \times 10^{-6}$	(2.200)	99.0
02	$0.02 \times 10^{-6}$	(0.004)	
$N_2$	$0.08 \times 10^{-6}$	(0.016)	1.0
Water	Trace	(Trace)	
Steam Desorbed Solid Amine			
CO <sub>2</sub>	$11.56 \times 10^{-6}$	(2.200)	94.4
02	$0.05 \times 10^{-6}$	(0.010)	0.5
$N_2$	$0.26 \times 10^{-6}$		2.1
Water	$0.37 \times 10^{-6}$	(0.070)	3.0




FIGURE 2 SX-1 SCHEMATIC

The water electrolyzer is designed so that the required water flow into the system is electrolyzed once through, thereby eliminating the need for a condenser/separator or a water recycle loop. From the water electrolyzer, the product 0, is plumbed directly to the SX-1 exhaust gas interface; byproduct H<sub>2</sub> is plumbed through a solenoid valve, SV108, to the SX-1 exhaust gas interface.

# Carbon Dioxide Electrolyzer and Recycle Loop

The feed gases are introduced through solenoid valve SV104 which remains open during normal operation. The recycle loop control technique has been designed to handle the expected fluctuations in feed gas flow from the EDC CO<sub>2</sub> Collection System. The CO<sub>2</sub> electrolyzer current will vary, dependent on recycle loop pressure as sensed by pressure transducer PS102. Increases in the flow rate of electrolyzable gases (CO<sub>2</sub> and water) to the system are compensated for in this manner. The gas flow is directed to the H<sub>2</sub> Separator, HSR101, where the excess H<sub>2</sub> in the feed gas is removed by selective diffusion through palladium/ silver (Pd/Ag) tubes. The gas is then plumbed into the recycle loop and directed to the CO<sub>2</sub> Electrolyzer Modules where CO<sub>2</sub> and the water vapor present in the recycle loop are electrolyzed. The net reactions are

$$CO_2 = CO + \frac{1}{2}O_2 \tag{5}$$

and

$$H_2^0 = H_2 + \frac{1}{2}O_2 \tag{6}$$

It is important to maintain a minimum of 3% water vapor and/or H<sub>2</sub> in the CO<sub>2</sub> electrolyzers since the presence of water vapor in the CO<sub>2</sub> Electrolyzer Module acts as a catalyst for the cathode reaction. Hydrogen has a similar catalytic effect; therefore, any combination of H<sub>2</sub> and water vapor equaling 3% of the feed gas composition to the CO<sub>2</sub> Electrolyzer Modules will catalyze the reaction. The presence of H<sub>2</sub> and/or water is maintained at 3% minimum by knowing the feed gas composition and by proper sizing of the H<sub>2</sub> Separator, HSR101. The recycle loop gases are then plumbed into the "on line" CO Disproportionator, COD101 or COD102. Since the CO disproportionation reaction

$$2CO = CO_2 + C \tag{7}$$

results in the formation of solid carbon which is collected in expendable CDCs, provisions are made to direct the recycle loop gas flow to alternate reactors. In this manner, the spent CDC can be removed and replaced without interrupting system operation. Hot Gas Valves HV101, HV102, HV103 and HV104 are manually operated to direct recycle loop gas flow to the desired CO Disproportionator. Since the off-line reactor will contain hazardous CO and  $\rm H_2$ , provisions have been made to evacuate and  $\rm N_2$  purge the reactor prior to changing the CDC. Electrical three-way valve, SV110, is used to select the reactor to be evacuated. On signal from the Control Instrumentation, solenoid valve SV111 is opened, thereby exposing the spent CO Disproportionator to vacuum.

After evacuation is complete, solenoid valve SV111 is closed. Prior to initiating cartridge change, the evacuated reactor is then filled with N<sub>2</sub> by opening solenoid valve SV106 and configuring electrical three-way valve SV107.

The recycle loop gases, after passing through the "on line" CO Disproportionator, are directed to the recycle loop  $\rm H_2$  Separator, HSR102, where the  $\rm H_2$  formed by the electrolysis of water in the feed gas is removed. The recycle loop gas then flows through the loop to the Recycle Loop Bellows Pump. The Bellows Pump, PlO1, maintains the recycle loop flow rate at 3.08 lpm (0.11 cfm). The recycle loop gas then exits the Bellows Pump and joins with the feed gas to complete the cycle.

# CO Disproportionator Feed Gas Fill

The feed gas is divided just before entering solenoid valve SV104. This line is directed to the CO Disproportionators through solenoid valve SV114 and electrical three-way valve SV107. This line allows filling of the off-line CO Disproportionator with feed gas prior to directing the recycle loop gas into it. This is done to avoid (1) a sudden drop in recycle loop pressure which would occur if the recycle loop gas flow was diverted to an evacuated CO Disproportionator, or (2) a buildup in recycle loop inerts which would occur if the CO Disproportionator is filled with  $N_2$  after CDC replacement.

# Nitrogen Purge

The system  $N_2$  purge is divided into four flow paths:

- 1. Through solenoid valve SV102 and flow restrictor FR101 for purging the  $\rm H_2$  gas compartment and associated plumbing of the water electrolyzer
- 2. Through solenoid valve SV106, flow restrictor FR102 and electrical three-way valve SV107 for purging the spent CO Disproportionator prior to replacing the CDC. Three-way valve SV107 is used to direct the flow to the desired CO Disproportionator
- 3. Through solenoid valve SV109 and flow restrictor FR104 for purging the  $\rm H_2$  exit line of the  $\rm H_2$  Separator
- 4. Through solenoid valve SV103 and flow restrictor FR103 for purging the feed gas inlet line and the recycle loop

Nitrogen is supplied through solenoid valve SV113 and pressure regulator RE101 for maintaining recycle loop pressure during Standby and Shutdown operating modes. Regulator RE101 allows  $N_2$  into the system so as to maintain recycle loop pressure above 0.17 x 10 $^4$  N/m $^2$  (0.25 psig).

The flow orifices used in the  $\rm N_2$  purge lines are incorporated to establish the  $\rm N_2$  flow rate and to provide overpressure protection for downstream components.

Pressure regulator RE102 and solenoid valve SV105 were added to the system to perform three functions:

- 1. To provide recycle loop overpressure protection. When pressure transducer PS102 senses pressure greater than 1.21 x  $10^4$  N/m² above ambient (1.75 psig), solenoid valve SV105 is opened and pressure regulator RE102 allows the recycle loop to vent until the pressure reaches 0.689 x  $10^4$  N/m² above ambient (1.0 psig). At the same time, the Control Instrumentation automatically configures the system to the Standby Mode.
- 2. To allow recycle loop  $N_2$  purge. In order to purge the recycle loop, the recycle loop pump is turned off and solenoid valve SV105 is opened, allowing  $N_2$  flow throughout the loop. Pressure regulator RE102 maintains backpressure at 0.70 x 10<sup>4</sup> N/m<sup>2</sup> above ambient (1.0 psig).
- 3. To allow the SX-1 to operate when interfacing with the feed gas of the Molecular Sieve and Steam-Desorbed Solid Amine CO<sub>2</sub> Collection Systems. Since the gas interface from these systems contains  $N_2$ , and since  $N_2$  does not enter into any of the loop reactions, a recycle loop pressure rise will occur as a result of the  $N_2$  buildup in the recycle loop.

It will be necessary to periodically vent the recycle loop when simulating the Molecular Sieve and Steam-Desorbed Solid Amine interface conditions. In order to accomplish this, solenoid valve SV105 will be periodically opened to relieve increases in recycle loop pressure due to the buildup of inerts  $(N_2)$ . This sequence will be initiated manually. Pressure regulator RE102 will allow the gas to vent until the loop pressure reaches  $0.70 \times 10^4 \text{ N/m}^2$  above ambient (1.0 psig). At this point the system will be manually configured back to the normal operating mode.

# Gas Exits and Sample Ports

The  $O_2$  outlet lines of the Electrolyzer Subassembly are kept separate for experimental test purposes. The  $O_2$  outlet lines from the  $CO_2$  electrolyzers are equipped with backpressure regulators (RE103, RE104 and RE105), pressure relief check valves (CV102, CV103 and CV104) and manual shutoff valves (V101, V102 and V103). The backpressure regulators in the  $O_2$  exit lines are included to maintain a 1.03 x 10 N/m above ambient (1.5 psig)  $O_2$  backpressure. This is required to minimize the  $\Delta P$  across the electrolyzer drums and to ensure that the pressure on the electrolyzer drum is greater on the  $O_2$  side. These provisions were incorporated due to the concern about the ability of the electrolyzer drum's precious metal seal to withstand up to a 1.2 x 10 N/m above ambient (1.75 psig) internal to external  $\Delta P$ . Check valves CV102, CV103 and CV104 are incorporated to provide overpressure protection in the event the pressure regulators fail closed. The check valves open at 1.38 x 10 N/m above ambient (2.0 psig). The  $O_2$  exit lines from the four electrolyzer modules

are plumbed separately so that an individual CO<sub>2</sub> Electrolyzer Module could be isolated from the system if desired. This provides operating flexibility in the event of a cell failure in any one of the CO<sub>2</sub> Electrolyzer Modules. The H<sub>2</sub> exit from the water electrolyzer is equipped with a solenoid valve, SV108. This valve is used to seal the H<sub>2</sub> lines and gas cavities of the Water Electrolyzer Module when it is not in operation. Gas sampling ports are provided downstream of the CO<sub>2</sub> Electrolyzer Modules (V104), downstream of the CO Disproportionators (V105) and downstream of the H<sub>2</sub> Separator (V106).

# Instrumentation

The SX-1 schematic shows the locations of all system sensors. These include thermocouples, thermistors, pressure transducers, differential pressure transducers, speed sensor, current and voltage sensors and valve position indicators. These are further discussed in the Instrumentation Section of this report.

# System Operating Modes

The SX-1 has four steady-state operating modes and one semiautomatic mode (CDC Change Mode) associated with the replacement of the CDC. The four steady-state modes are Shutdown, Standby, Normal and Purge. A description of each operating mode follows.

# Shutdown Mode

In the Shutdown Mode the system is not performing the function of converting  $\rm CO_2$  and water vapor to  $\rm O_2$ . In addition, all system heaters for the Electrolyzer Modules,  $\rm CO$  Disproportionator,  $\rm H_2$  Separators and the Water Feed Mechanism are turned off. The Electrolyzer Modules have their currents removed, valves are in their de-energized state which closes the gas supply valves to prevent the flow of supply gas and the Recycle Loop Bellows Pump is not circulating gas within the recycle loop. The output from the  $\rm H_2$  Separator is isolated from vacuum; however, the recycle loop is exposed to vacuum via a backpressure regulator, RE102 (see Figure 2), to ensure that, even when in the Shutdown Mode, loop pressure does not exceed 1.21 x  $\rm 10^4~N/m^2$  above ambient (1.75 psig). As insurance that the recycle loop pressure does not drop below 0.17 x  $\rm 10^4~N/m^2$  above ambient (0.25 psig), the loop is opened to the  $\rm N_2$  purge gas supply via another pressure regulator, RE101. From the Shutdown Mode a significant period of time must elapse before the system can be operated because the hot components have to be slowly heated to operating temperature.

## Standby Mode

In the Standby Mode, as in the Shutdown Mode, the system is not performing the function of converting CO and water vapor to  $O_2$ . The major difference between the two modes is that in Standby the heaters are operating, keeping the Electrolyzer Modules, CO Disproportionator,  $H_2$  Separators and the Water Feed Mechanism at temperature and the Recycle Loop Bellows Pump is not operating. Two other variations are that the output from the  $H_2$  Separator (SV112) is opened to vacuum and the recycle loop is isolated from vacuum (SV105) under the normal

steady-state conditions of this mode. Only if the recycle loop pressure exceeds 1.21 x  $10^4$  N/m² above ambient (1.75 psig) will this loop be opened to vacuum via backpressure regulator RE102. All other functions hold true as outlined above in the Shutdown Mode definition. From the Standby Mode the system can be put into operation in less than five minutes.

## Normal Mode

In the Normal Mode, the system is performing its intended function of converting the CO<sub>2</sub> and water vapor to O<sub>2</sub>. All monitored parameters are within allowable limits.

As the system operates, carbon will build up in the CO Disproportionator that is "on line." This CO Disproportionator will have to be isolated from the recycle loop and a second CO Disproportionator put "on line." This semiautomatic CO Disproportionator exchange mode is detailed below. Also, in the Normal Mode, if the recycle loop pressure exceeds 1.21 x 10 N/m above ambient (1.75 psig), the loop will be opened to vacuum via a backpressure regulator, RE102.

# Purge Mode

In the Purge Mode the system is not performing the function of converting  ${\rm CO}_2$  and water vapor to  ${\rm O}_2$ . All N<sub>2</sub> purge valves (SV113, SV102, SV103, SV109, SV107, SV106) are configured to permit a N<sub>2</sub> purge to all recycle loop components and the H<sub>2</sub> exhaust line of the Water Electrolyzer Module. Solenoid valve SV113 remains open at the conclusion of the N<sub>2</sub> Purge sequence and thereby allows RE101 to compensate for any underpressure situation in the recycle loop. Similarly, SV105 remains open and allows RE102 to compensate for any overpressure condition that might occur in the recycle loop.

## Carbon Deposition Cartridge Change Mode

In addition to the operating modes described above, the SX-1 contains a semi-automatic CO Disproportionator Cartridge Change Mode. This mode provides for isolating a carbon-filled CO Disproportionator from the recycle loop and putting the second unfilled CO Disproportionator "on line." The operating sequence for the semiautomatic CO Disproportionator Cartridge Change is discussed later in this report as part of the Control Instrumentation Description.

#### SYSTEM HARDWARE DESCRIPTION

The SX-1 consists of 58 components mounted on a welded unistrut frame. Figure 3 is a front view of the assembled SX-1. Table 3 lists the SX-1 components. Six of these were designed, fabricated and assembled under the program. The remainder of the components were off-the-shelf and were selected for the application. These are solenoid valves, pressure regulators, pressure transducers, check valves, Hot Gas Valves, a Bellows Pump and flow restrictors. Following is a discussion of the six major components designed, developed, fabricated and assembled during the program.




FIGURE 3 FRONT VIEW OF ASSEMBLED SX-1

TABLE 3 SX-1 COMPONENTS LIST

Item	Quantity Required	Part Number	Description/Title/Name
1	3	CE101 thru CE103	Module, Electrolyzer, CO <sub>2</sub>
2	1	HE101	Module, Electrolyzer, Water
3	2	COD101, COD102	Disproportionator, CO
4	2	HSR101, HSR102	Separator, H <sub>2</sub>
5	1	C101	Instrumentation, Control
6	1	M101	Instrumentation, Monitor
7	1	P101	Pump, Bellows
8	8	SV103, SV105, SV106, SV102, SV109, SV111, SV113, SV114	Valve, Shutoff, Electrical Normally Closed
9	4	SV101, SV104, SV108, SV112	Valve, Shutoff, Electrical, Normally Open
10	2	SV107, SV110	Valve, 3-Way, Electrical
11	4	HV101 thru HV104	Valve, Hot Gas
12	7	V101 thru V107	Valve, Shutoff, Manual
13	5	CV101 thru CV105	Valve, Check
14	5	RE101 thru RE105	Regulator, Pressure
15	1	PR101	Regulator, Pressure, Pressure Referenced
16	1	FB101	Mechanism, Water Feed
17	5	FR101 thru FR105	Restrictor, Flow
18	2	PS102, PS105	Transducer, Pressure
19	3	PS101, PS103, PS104	Transducer, Pressure Differential

### Electrolyzer Subassembly

The electrolyzer subassembly consists of four major parts. The electrolyzer furnace, with built-in heaters and insulation; three CO<sub>2</sub> Electrolyzer Modules; one Water Electrolyzer Module; and the associated plumbing and wiring connections.


# Electrolyzer Furnace

The function of the electrolyzer furnace is to heat and maintain the CO, and Water Electrolyzer Modules at their operating temperature. The assembly drawing showing the location of the electrolyzer furnace is shown in Figure 4. The materials of construction and operating characteristics of the electrolyzer furnace are listed in Table 4. The furnace is a self-supporting unit consisting of a welded structural frame, gas manifolding, heaters, insulation, stainless steel covers and module access doors. The frame is used to support the modules, heaters and gas manifolding. The electrolyzer modules are supported inside the Inconel muffles (horizontal tubes) with the ceramic heaters attached to the outside. The muffle support plates are welded to the 302 stainless steel unistrut channel. The process gas manifolding is welded to the frame channel with a tube fitting at each end. The tube fitting and metal bellows allow for a frame and module differential thermal expansion and simple module removal from the electrolyzer furnace. The stainless steel frame is completely enclosed with insulation for minimum heat loss. The only contact the frame has with the external covers is at the mounting pads on the bottom surface and at the flanged front face with the access doors. The insulation material is protected externally by the stainless steel covers and internally at the service area with a muffle support plate and front face flanges. The insulation thickness was selected to give an external cover operating temperature of less than 322K (120F). The insulation thickness required to achieve this outer skin temperature was calculated to be 20.3 cm (8.0 in). The furnace assembly includes Bakelite terminal blocks for power and thermocouple lead connections on the back cover.

# Electrolyzer Modules

The function of the electrolyzer modules is to convert  ${\rm CO}_2$  to  ${\rm CO}$  and  ${\rm O}_2$  and to convert water into  ${\rm H}_2$  and  ${\rm O}_2$ .

The CO<sub>2</sub> and Water Electrolyzer Modules that were incorporated into the electrolyzer Subassembly were based on the results of a development effort sponsored by the NASA Ames Research Center under Contracts NAS2-2870, NAS2-4843 and NAS2-6412. This work was reported to result in CO<sub>2</sub> electrolysis cells that provide breathable O<sub>2</sub> containing less than 1% impurities and that operate at 100% Faradaic current efficiency. A 12-cell (six-drum) module has demonstrated operation for 101 days. The CO<sub>2</sub> and Water Electrolyzer Modules contain eight electlyzer drums. Each electrolyzer drum contains two electrolysis cells as shown in Figure 5. The electrolyzer drum is a cylinder with a diameter of 6.3 cm (2.48 in) and a height of 1.0 cm (0.39 in). Each cell contains two fully stabilized zirconium oxide electrolyte disks with active platinum (Pt) elec-



Explanation of numbers in circles on page 20.

continued-

FIGURE 4 COMPLETE ELECTROLYZER FURNACE ASSEMBLY

Figure 4 - continued

7 1	181- D-1047	ACTUATOR ASS'Y	SEE DETAIL	<b>LS</b> /	32
	LS1- D-1074	SWITCH (REAR) ASS'Y	SEE DETAIL	251	3/
	LS/- D-1073	SWITCH (FRONT)AST		<b>LS</b> /	30
	LSI- E-1037	CASSIS ASSY	SEE DETAIL	25/	29
20	LS/- J-990-13	LOCK WASHER, SPAWE	#10 ~ S/STX	INSTOCK FASTEMENTS	28
12	131-J-990-12	NUT, HEX REG	#10-32 ~ 3/574	INSTUCK FASELLES	22
1	LS/- D-984-1	TOP PANEL	SEE DETAIL	23/	26
/	131-D-984-2	REAR PANEL (ELECT)	SEE DETAIL	<i>L31</i>	25
2	151-D-984-4	SIDE PANEL (ELECT)	SEE DETAIL	251	24
/	LS/- D-984-3	FRONT PANEL (ELECT)	SEE DETAIL	251	23
2	LSI-J- 990-10	CABLE RETRACTOR	CR-200	ZERO MG CO	22
12	131- J-990-11	SCREW, RD HD MAC	*1032 x 1.7516 ~ S/STL	INSTOCK FASTEURS	21
AR	LSI- J- 990-9	SHIM	.015 THICK ~ STEEL	181	20
34	151- J- 990-8	SCREW, RD HD MAC	#10-32 x .75 16 ~ \$/571	INSTOCK FATTENERS	19
//	LSI- J-990-7	TERMINAL BOARD	* 1215-3	KULKA ELECT CO	18
6	LS/ - J- 990-6	TERMINAL BOARD	<i>* 1215-2</i>	KULKA ELECTCO	17
/	191-0-989	COVER, TEAM BOARD	SEE DETAIL	181	16
2	151-0-984-5	PANEL, SIDE	SEE DETAIL	151	15
	181-5-990-5		CTRD-224	ZERO MFG CO	14
/	LSI-D-987	INTERFACE PANEL	SEE DETAIL	181	13
/	LSI-D- 971	HA SEP HINGED DOOR ASSY	SEE DETAIL	151	12
/	181-0-975	CO DIS ACCESS COVERAN	SEE DETAIL	191	11
/	LS/- J- 986	FURNACE SUB-ASSY	. SEE DETAIL	L3/	10
/	LSI- C-981	DOOR STOP CHANNEL	SEE DETAIL	181	9
36	LSI-J- 990-4	SCREW, PAN HO	#10 TYPE TYPE 8 SOCTOP	INSTOCK FASTENERS	8
2	131-0-982	DOOR STOP, UPPER W	SEE DETAIL	131	7
2	LS/-	INSULATION	SEE DETAIL	18/	6
/	LS1-E-1009	CHASSIS ASSY	SEE DETAIL	131	5
8	LS/-J- 990-3	SCREW, RD HD MACH	410-32 x .38 46 ~ 9/572	INSTOCK FATEURS	4
26	131-5-990-2		*14-20 x .5016 ~ 8/57L	INSTOCK PASTEMEN	3
4	LS1-J- 990-1	SWIVEL -PLATE CASTERS		W.W. GRAINGER	2
	151-5-813	MAIN FRAME ASSY	SEE DETAIL	131	1
QT'Y REQ'D	PART OR IDENTIFYING NO.	NOMENCLATURE OR DESCRIPTION	MATERIAL AND SPECIFICATION	REFERENCE OR NOTE	ITEM NO.
		LIST OF MATERI	ALS OR PARTS LIST	T	
DFTM.	M. PROKOP	8-5-74	Life Systems,	Inc.	
CHKR.	M. Propycak	1-8-75 TITLE	CLEVELAND, OHIO		
ENGRG. APPD.	5. Mohake	1-8-75 ASS	SY, ELECTROLYZER	?	
APPROVA		- 1-9-75	FURNACE		
DIMEN TOL. ON TOL. ON	OTHERWISE SPECIFII SIONS ARE IN INCHES ANGLES ± I TWO-PLACE DEC. I THREE-PLACE DEC.			- 990	

# TABLE 4 SX-1 ELECTROLYZER FURNACE OPERATING CHARACTERISTICS AND MATERIALS

Characteristics	Description
Overall Size, cm (In)	125.9 x 59.2 x 80.8 (49.5 x 23.3 x 31.8)
Power (Heaters), V	230, 1400 W/each
Temperature, K (F)	1123 (1562)
Process Gas Tube Interfaces, cm (In)	0.950 (0.375) stainless steel tube fittings
Access Area Opening, cm (In)	87.0 x 33.0 (34.2 x 13.0)
Materials	
Frame	Standard Unistrut 302 stainless steel channel A5000 and A1000, Inconel 600 muffles
Covers, cm (In)	0.127 (0.050) 304 stainless steel
Insulation	Standard Johns-Manville Micro Quartz
Heaters	Standard Lindberg Model 50531, Type 5712-SP, Ceramic Clam Shells, eight required
Fittings, cm (In)	Standard Swagelok stainless steel, 0.950 (0.375) union tube fittings




FIGURE 5 ELECTROLYZER DRUM

trodes integrally attached to both sides of each disk. The active area of each cell is 20 cm<sup>2</sup> (3.10 in<sup>2</sup>). The electrolyzer subassembly contains four electrolyzer modules. Three CO<sub>2</sub> Electrolyzer Modules are plumbed into the recycle loop. The fourth electrolyzer module is fed separately with water vapor and is utilized to electrolyze water in a once-through fashion. The operating characteristics of the electrolyzer modules are listed in Table 5. The electrolyzer modules are packaged by enclosing a set of eight drums in a gas-tight 304 stainless steel or Inconel 600 can. The heating elements and all furnace insulation material are external to the can. This packaging tecnique has been described as the Internal Can Concept. (13)

A photo of a completed electrolyzer module is shown in Figure 6. The inlet and outlet manifold tubes shown are constructed with bellows to allow easy electrolyzer module removal and replacement within the confinement of the fixed system plumbing. They also allow for thermal deflections that occur as the system comes up to temperature. The O<sub>2</sub> outlet manifold tube is a branch of one of the electrical conductor support tubes described next. The nine tap wires and two current conductors come out of the modules in groups of 4, 4, and 3 in the three electrical conductor tubes indicated. They are supported and insulated from each other in the system manifolding by the use of four-hole alumina insulators. These insulators run the full length of the tube. thermocouple wells are close-ended and spaced at the proper axial distance inside the can assembly. Since they are close-ended tubes and the thermocouples enter from outside of the module, no penetration or discontinuity in the electrolyzer module boundary exists. This feature allows for in situ maintenance of thermocouples without the need for cooling down the system and disassembling the electrolyzer modules. The major components of the module, as shown separated in Figure 6, are the module can assembly, including the 0, manifold end cap, thermocouples, and electrical connectors and the electrolyzer drums and manifold assembly. The module can assembly seal is an Inconel O-ring seal that is held in place and compressed by the use of 12 equally spaced Inconel screws holding the cover to the module can assembly. The seal for the electrical connectors is a bulkhead seal located at the end of the electrical conductor tubes. This seal is made by use of a crushable lava spacer. The thermocouples do not require a boundary seal since they are externally inserted into the tubes that are welded to the end cap. The electrolyzer drum supports and the two alumina manifold tube supports are both made from fired lava.

The materials used in the electrolyzer module assembly were chosen for their resistance to the expected recycle loop gases (CO, CO<sub>2</sub>, H<sub>2</sub> and water) at the maximum operating temperature of 1173K (1652F). Where required, electrical conductivity and thermal expansion considerations were included. Inconel 600 is used for the can assembly and the 1.27 cm (0.5 in) diameter external manifold tubes and electrical conductor support tubes. The 0.95 cm (0.375 in) diameter internal manifold tubes are made out of alumina tubing closed on one end. The tubulations used to connect the drums to the alumina manifold tubes are Pt/10% iridium (Ir) alloy. The tap wires and conductors are made of gold (Au)/3.5% Pd alloy.

# TABLE 5 ELECTROLYZER SUBASSEMBLY PERFORMANCE CHARACTERISTICS

# Carbon Dioxide Electrolyzer

Feed Gas Composition, kg/s (Lb/Hr), %	_
CO <sub>2</sub> CO <sup>2</sup> H <sub>2</sub> Water	9.317 x 10 <sup>-5</sup> (0.7389), 51.60 5.217 x 10 <sup>-5</sup> (0.4137), 45.40 0.010 x 10 <sup>-5</sup> (0.0019), 2.86 0.010 x 10 <sup>-6</sup> (0.0008), 0.14
Wáter	0.010 x 10 (0.0008), 0.14
Feed Gas Temperature, K (F)	628 to 658 (670 to 725)
Feed Gas Pressure, N/m <sup>2</sup> (Psia)	$10.3 \times 10^4$ to $11.0 \times 10^4$ (15 to 16)
Current (Total), Cell A	102
Current Density (48 Cells), mA/cm <sup>2</sup> (ASF)	106 (98.5)
Current per Module, A	2.1
Operating Temperature, K (F)	1143 to 1163 (1598 to 1634)
•	
Water Electrolyzer	
Water Electrolyzer Feed Gas. kg/s (Lb/Hr)	
	$0.285 \times 10^{-5} (0.542)$
Feed Gas. kg/s (Lb/Hr)	$0.285 \times 10^{-5} (0.542)$ 397 to 402 (255 to 264)
Feed Gas. kg/s (Lb/Hr) Water Vapor	
Feed Gas. kg/s (Lb/Hr) Water Vapor Feed Gas Temperature, K (F)	397 to 402 (255 to 264) 10.1 x 10 <sup>4</sup> to 11.7 x 10 <sup>4</sup>
Feed Gas. kg/s (Lb/Hr) Water Vapor Feed Gas Temperature, K (F) Feed Gas Pressure, N/m <sup>2</sup> (Psia)	397 to 402 (255 to 264)  10.1 x 10 <sup>4</sup> to 11.7 x 10 <sup>4</sup> (14.7 to 17)  30.5
Feed Gas. kg/s (Lb/Hr) Water Vapor  Feed Gas Temperature, K (F)  Feed Gas Pressure, N/m <sup>2</sup> (Psia)  Current (Total), Cell A	397 to 402 (255 to 264)  10.1 x 10 <sup>4</sup> to 11.7 x 10 <sup>4</sup> (14.7 to 17)  30.5




FIGURE 6 ELECTROLYZER MODULE

#### CO DISPROPORTIONATOR

The function of the CO Disproportionator is to convert the SX-1 system recycle loop CO gas to CO<sub>2</sub> and solid carbon in the presence of a carbon steel (AISI 1025) catalyst, with the addition of heat. The reaction taking place in the CO Disproportionator is

$$2CO = CO_2 + C \tag{8}$$

A disassembled CO Disproportionator is shown in Figure 7. The CO Disproportionator consists of a housing assembly and a replaceable CDC assembly. The CDC consists of a front and rear end cap filter and screen, a catalyst star, the CDC housing, and the cover assembly with handles provided for ease of CDC removal and replacement. For a cartridge change, the CDC is pulled from the housing assembly utilizing the two handles. The CDC is then disassembled and the formed carbon and remaining catalysts are disposed of. A new catalyst star is obtained and the CDC is reassembled and inserted into the housing The process gas enters the CO Disproportionator at the inlet manifold tube shown in Figure 7. It then passes through the front cartridge end cap, filter and screen, and reacts in the presence of the star-shaped catalyst. The solid carbon forms on the surface of the star catalyst with the formed CO2 passing through the rear cartridge end cap, filter and screen, and into the recycle loop. The main CO Disproportionator seal is an O-ring seal made from copper-clad Inconel. This fits between the cover assembly and the cylindrical outer housing. When the quick-disconnect clamp is fastened around the cover and main body assembly, the seal is formed. Leakage or parallel passage of gas between the CDC and housing assembly is prevented by two wire seals placed around the ends of the CDC assembly. The other end of the CO Disproportionator housing assembly is secured by welding, thus no seals are required at this end.

A literature survey was performed to determine what materials could be used for construction of the CO Disproportionator. Based on material availability, ease of fabrication and cost, electroless nickel-plated stainless steel was selected as the base construction material. As a result, all metal components other than the star catalyst have been plated with 0.0025 cm (0.001 in) thick electroless nickel to prevent the CO Disproportionation reaction from occurring on these surfaces. Table 6 lists the CO Disproportionator operating characteristics and materials.

# H, SEPARATOR

The function of the  $H_2$  Separator is to remove excess  $H_2$  from the feed and recycle loop gases. Figure 8 shows a sectioned view of the completed design. The process gas enters the vertical tube and exits through the horizontal tube at the right of the assembly. A vacuum is drawn through the horizontal tube at the left side of the assembly and on the inside of the commonly manifolded Pd/Ag tubes. The Pd/Ag tubes are concentrically packed and welded into a header assembly which is metal 0-ring-sealed and bolted to the external housing.





FIGURE 7 CO DISPROPORTIONATOR

# TABLE 6 SX-1 CARBON MONOXIDE DISPROPORTIONATOR AND CATALYST ACTIVATION FURNACE OPERATING CHARACTERISTICS AND MATERIALS

Characteristics	Description
Overall Size, cm (In)	24.76 x 76.2 (9.75 x 30.0)
Power (Heaters), V	115, 875 W/each
Temperature, K (F)	823 (1022)
Process Gas Tube Interface, cm (In)	0.950 (0.375) stainless steel tube fitting
Materials	
Housing, cm (In)	Standard 20.3 (8.0) Schedule 40 304 stainless steel pipe, electroless nickel plated (0.0025 (0.001))
CDC Housing, cm (In)	0.150 (0.059) 316 stainless steel, electroless nickel plated (0.0025 (0.001))
CDC Catalyst, cm (In)	Standard 0.013 (0.005) A1S1 1025 sheet steel
CDC Filter	Standard Fiberfrax LO-CON ceramic fiber
CDC End Caps, cm (In)	20.3 (8.0) round 304 stainless steel, electroless nickel plated (0.0025 (0.001))
CDC Screen, cm (In)	Stainless steel 8 x 8 mesh, electroless nickle plated (0.0025 (0.001))
Heaters	Standard Lindberg Model 50821, Type 8708-SP, Ceramic Clam (1/4) Shell, twelve required
Fittings, cm (In)	Standard Swagelok union tee 600-3-316, electroless nickel plated (0.0025 (0.001))

## FIGURE 8 H2 SEPARATOR



Based on the theoretical expression, relating diffusion rate, Pd/Ag tube diameter, Pd/Ag tube wall thickness, and Pd/Ag tube length, it was determined that 12.19 m (40 ft) of 0.159 cm (0.062 in) diameter and 0.0076 cm (0.003 in) wall Pd/Ag tubes were required.  $^{(16)}$  This requirement was based on a 75% Pd/25% Ag alloy and an operating temperature of 616K (650F).


One common design is used for both the recycle loop and the feed gas  $\rm H_2$  separators. Figure 9 is a picture of a disassembled  $\rm H_2$  Separator. The  $\rm H_2$  Separator operating characteristics and materials of construction are listed in Table 7.


#### WATER FEED MECHANISM

The function of the Water Feed Mechanism is to provide a stable and constant flow of super-heated steam to the Water Electrolyzer Module. The steam is required as a source of additional 0, to make up the difference between the 0, available from CO, and that metabolically required by man. The Water Feed Mechanism consists of the following major components: heater, tube, orifice, thermocouples and temperature control which is part of the Control Instrumentation. The Water Feed Mechanism consists of three specific stages: preheater, flash orifice, and a boiler. In the preheater stage, the water temperature is rajsed along its length to a liquid saturation temperature of 407K at 31.0 x  $10^4~\mathrm{N/m}^2$  (274F at 45 psia) and maintains that level at the orifice entrance by a thermocouple and temperature control. This corresponds to Point 1 on Figure 10, which is a plot of temperature versus distance along the flash boiler tube. The super-heated water is flashed through the orifice to the low pressure, 10.3 x 104 N/m2 (15 psia), side of the Water Feed Mechanism (Point 4). As the water passes through the orifice, it undergoes a phase change from liquid to vapor. However, not all the liquid is transformed into vapor at the orifice and as a result more heat energy must be applied in the boiler section to achieve a complete change to the vapor phase (Point 3). However, a large enough phase change of liquid to vapor is achieved at the orifice (90% by volume) to yield a uniform and constant steam flow mode. A drawing of the Water Feed Mechanism with callouts describing the individual components is shown in Figure 11.

#### CONTROL INSTRUMENTATION

The primary functions of the Control Instrumentation are to provide the logic and programming for system mode transitions, to control Normal Mode operation by automatically varying the CO<sub>2</sub> Electrolyzer Module's current as a function of recycle loop pressure, and to control all other parameters critical to the system operation, such as Electrolyzer Module temperature, CO Disproportionator temperature, H<sub>2</sub> Separator temperature, Water Feed Mechanism temperature, Water Electrolyzer Module current, and Recycle Loop Bellows Pump speed. A listing of the parameters, their controlling functions, and all internal adjustments, is presented in Table 8. The SX-1 has four steady-state operating modes and one semiautomatic mode. The latter is associated with the replacement of the CDC. The allowed mode transitions are described in Figure 12. The flow chart describing the sequencing for mode transitions is presented in Appendix 1.






# TABLE 7 SX-1 HYDROGEN SEPARATOR OPERATING CHARACTERISTICS AND MATERIALS

Characteristics	Descript	Description		
Overall Size, cm (In)	8.6 x 63.0 (3.4 x 25.0)			
Hydrogen Diffusion Area, cm <sup>2</sup> (In <sup>2</sup> )	606.0 (94.0)			
Process Gas Inlet				
Temperature, K (F) Pressure, N/m <sup>2</sup> (Psia)	616 (650) <sub>4</sub> 10.3 x 10 <sup>4</sup> (15)			
	Feed Gas	Recycle Gas		
Flow Rate, Sccm (Scfm)/Min Composition, % V	505.6 (0.018) 75.20 CO <sub>2</sub> 1.67 Water 23.13 H <sub>2</sub>	2696.2 (0.095) 32.19 CO 64.39 CO 3.42 H <sub>2</sub> 0 Water		
Power, W	175			
Tube Interface, cm (In)	0.95 (0.375) diameter stainles steel tubing			
Materials				
Housing	304 stainless st	teel		
Separator Tubes	Pd/Ag Alloy (75/25)  Advanced Products Company, 1375-3-3-CP-PF			
O-Rings				
Heaters	Lindberg Model	50031, Type 77-SP		

FIGURE 10  $H_2^{O}$  TEMPERATURE VERSUS FLASH BOILER TUBE LENGTH






FIGURE 11 WATER FEED MECHANISM

_	Con	trolled Parameter	Controlling Function	Adjustments
	1	(a) FB101 Flash Boiler Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermistor TS 127. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure.
·	2.	HE101 Water Electrolyzer Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 101. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the four electrolyzers has a separate set point adjustment.
35	3.	CE101 CO <sub>2</sub> Electrolyzer Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 105. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the four electrolyzers has a separate set point adjustment.
	4.	CE102 CO <sub>2</sub> Electrolyzer Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 109.  Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the four electrolyzers has a separate set point adjustment.
	(a)	See Figure 2, page 10, for so	ensor locations.	continued-

C	ontrolled Parameter	lled Parameter Controlling Function	
5.	CE103 CO <sub>2</sub> Electrolyzer Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 113. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the four electrolyzers has a separate set point adjustment.
, 6.	COD101 CO Disproportionator No. 1 Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 117. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the two disproportionators has a separate set point adjustment.
7.	COD102 CO Disproportionator No. 2 Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 121. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. Each of the two disproportionators has a separate set point adjustment.
8.	HSR101 H <sub>2</sub> Separator Temperature	Error signal representing the difference between the desired set point temperature and the true temperature as measured by thermocouple TS 126. Proportional Control.	Desired set point temperature is a potentiometer setting inside the system control instrumentation enclosure. The feedback temperature measurement may come from either TS 126 or TS 128.
			continued-

Life Systems, In

SX-1 STEADY STATE CONTROLLED PARAMETERS

Controlled Parameter Control		Controlling Function	Adjustments
9.	HE101 Water Electrolyzer Voltage/Current	Manual set point for desired applied voltage.  Manual set point for desired max. current limit.	Desired module applied voltage is a potentiometer setting within the control instrumentation enclosure. Desired module max. current limit is a potentiometer setting within the control instrumentation enclosure.
10. 37	CE101 CO, Electrolyzer Voltage/Current	Manual set point for desired max. voltage limit.  Current controlled by recycle loop pressure in the automatic mode, by a manual set point in the manual mode. Proportional Control.	Desired module max voltage limit is a potentiometer setting within the control instrumentation enclosure. In the automatic mode, there are potentiometer settings to adjust the steady state current/pressure operating point, the current vs pressure loop gain, and the desired max. current limit. All these adjust ments are within the control instrumentation enclosure. In the manual mode, there is a potentiometer setting for the desired electrolyzer current. This too is within the control instrumentation enclosure.
			continued-

# SX-1 STEADY STATE CONTROLLED PARAMETERS

Controlled Parameter	Controlling Function	Adjustments	
11. CE102 CO <sub>2</sub> Electrolyzer Voltage/Current	Manual set point for desired max. voltage limit.  Current controlled by recycle loop pressure in the automatic mode, by a manual set point in the manual mode. Proportional Control	Desired module max. voltage limit is a potentiometer setting within the control instrumentation enclosure.  In the automatic mode, there are potentiometer settings to adjust the steady state current/pressure operating point, the current vs pressure loop gain, and the desired max current limit. All these adjust ments are within the control instrumentation enclosure. In the manual mode, there is a potentiometer setting for the desired electrolyzer current. This too is within the control instrumentation enclosure.	
12. CE103 CO, Electrolyzer Voltage/Current	Manual set point for desired max. voltage limit.  Current controlled by recycle loop pressure in the automatic mode, by a manual set point in the manual mode. Proportional Control.	Desired module max. voltage limit is a potentiometer setting within the control instrumentation enclosure.  In the automatic mode, there are potentiometer settings to adjust the steady state current/pressure operating point, the current vs pressure loop gain, and the desired max current limit. All these adjustments are within the control instrumentation enclosure. In the manual mode, there is a potentiometer setting for the desired electrolyzer current. This too is within the control instrumentation enclosure.  continued-	

Life Systems, In

SX-1 STEADY STATE CONTROLLED PARAMETERS

Controlled Parameter	olled Parameter Controlling Function	
13. P101 Recycle Loop Pump Speed	Error signal representing the difference between the desired set point pump speed and the true pump speed as measured by speed sensor SS 101.	Desired set point pump speed is a potentiometer setting inside the system control instrumentation enclosure.
14. P102 Recycle Loop Pump Speed	Error signal representing the difference between the desired set point pump speed and the true pump speed as measured by speed sensor SS 102.	Desired set point pump speed is a potentiometer setting inside the system control instrumentation enclosure.
20		
·		





FIGURE 12 SX-1 ALLOWED MODE TRANSITIONS

The flow chart consists of the main program which calls upon five separate subroutines describing the Purge, Normal, Reactor Change, Standby, and Shutdown sequences. In order to follow the flow chart it is necessary to refer to the system schematic which is included as Figure Al-1. The operations described in the flow chart are completely automatic with the exception of the Reactor Change Mode and system startup. In these two cases manual intervention is required. For the Reactor Change Mode, manual intervention is required to configure the Hot Gas Valves in the recycle loop to allow CO<sub>2</sub> Disproportionator switchover and servicing. The manual operations are described in detail in Appendix 1.

To start the system, the operator first depresses the Purge Pushbutton and then the Normal Pushbutton which initiates the automatic sequence as described in Appendix 1. The pushbuttons are shown in Figure 13 which is a picture of the completed Control Instrumentation. The Control Instrumentation is contained in a pull-out drawer mounted within the framework of the SX-1. The system control panel is the front of the drawer. The Control Instrumentation contains 20 printed circuit (PC) cards and these are described in Table 9. The Control Instrumentation also contains four power supplies, 28 photo isolated power relays, 19 manual override switch assemblies, a shutdown counter and an elapsed time meter, and four electrical connectors. The Control Instrumentation's front panel is pictured in Figure 14. This photograph shows the recessed panel with the safety cover removed, revealing a cluster of manual override switches and current control potentiometers and the pump speed control potentiometer. Also indicated on the front panel are the Mode Command Pushbuttons, the CO Disproportionator status indicator and pushbuttons, and the elapsed time meter and event counters. Also present is an override indicator which is used to indicate that any one of the system prime movers are in a manual override condition and a Lamp Test Pushbutton to verify the operation of the lamps in the indicators.

#### MONITOR INSTRUMENTATION

The SX-1 Monitor Instrumentation functionally provides for three things: (1) the display of Trend and Fault Analysis information, (2) the protection of the system by automatic shutdown or standby, and (3) the conditioning of system sensor signals prior to their being sent to ground support equipment for display in engineering units. In the first of these functions, the Monitor Instrumentation collects signals from the important system sensors, conditions these sensor signals and displays the results with illuminated indicators on the Performance Trend and Fault Analysis Panel. The Performance Trend and Fault Analysis Panel is shown in Figure 15, which is a picture of the Monitor Instrumentation package. The indicators on the Performance Trend and Fault Analysis Panel provide the following information:



# FIGURE 13 CONTROL INSTRUMENTATION

Life Systems, Inc.

TABLE 9 CONTROL INSTRUMENTATION PC CARD LIST

Qty.	Card No.	Title	Functions
4	A13	Current/Voltage Control (Electrolyzer Modules)	Controls current in electrolyzer cells.
1	AC17	Automatic Slew Control	Generates 276K (37.4F)/Min ramp for Electrolyzer Module temp. control.
4	AC18-1	Temperature Control (Electrolyzer Modules)	Controls Electrolyzer Module temp.
1	AC18-2	Temperature Control (Flash Boiler)	Controls Flash Boiler temperature.
4	AC18-3	Temperature Control (CO Disproportionators and $H_2$ Separator)	Controls CO Disproportionator and H <sub>2</sub> Separator Temperatures.
1	AC19	Power Switch/Latch	Power driver stage and enable/disable logic electrolyzer module current controllers.
1	AC20	Pump Speed Control	Controls the speed of the recycle loop pump motor.
1 .	AC21	Main Sequencer "A" (Input Multiplexer)	Multiplexes and latches input signals for sequence generator.
1	AC23	Main Sequencer "C" (Sequence Generator)	Generates sequential control of system
1	AC24	Main Sequencer "D" (System Clocks & Timers)	Generates system clock and required timeouts.
1	AC25	Main Sequencer "E" (Output Decoder/Driver)	Decodes inputs from sequence generator and drives required output.




FIGURE 14 CONTROL INSTRUMENTATION FRONT PANEL




FIGURE 15 MONITOR INSTRUMENTATION

Condition	Color	Response	
Normal	Green	No response needed.	
Caution	Amber	Condition developing that could result in a hazardous situation; predetermined response necessary but not necessarily time critical.	
Warning	Flashing Red	Hazardous condition developing in which urgent action is required by the operator (crew) to avoid an alarm or other serious situation. Predetermined action by operator required, but by direction of lead engineer rather than by automatic reaction.	
Alarm	Red	Condition exists causing automatic system shutdown. If a shutdown does not occur, emergency response by the operator is required and predetermined reaction is necessary.	

The Performance Trend and Fault Analysis Panel provides the operator of the system with an advanced warning of a parameter moving out of its acceptable operating range and thus allows for the operator to modify system operation to correct for this parameter deviation. The panel further aids detecting and isolating faults in the system when problems do occur.

In the second of these functions, the Monitor Instrumentation provides for automatic system shutdown or standby when a parameter or group of parameters deviate from safe ranges and when such deviations can potentially cause personnel injury or equipment damage. Table 10 lists the SX-1 shutdown causes, possible malfunctions that can cause such shutdowns, shutdown trip levels and the final mode in which the system is automatically placed.

The final function of the Monitor Instrumentation is to condition sensor signals for the ground support display. This conditioning consists of amplification, attenuation, filtering, and scaling of sensor information so that the ground support data can be displayed in engineering units. Table 11 shows the parameters monitored during SX-1 operation, and whether these parameters are monitored on the Performance Trend and Fault Analysis Panel or the Ground Support Panel. The component and sensor identification numbers listed in Table 11 refer to the system schematic which is presented in Figure 2.

The Monitor Instrumentation electronics is contained in a pull-out drawer which is mounted within the framework of the SX-1. The Performance Trend and Fault Analysis Panel is the front of the drawer. Contained within the drawer are all required PC cards, all bias power supplies, all Monitor Instrumentation input/output connectors and 25 switches which allow the system operator to individually inhibit each of the 25 system shutdown protections. Table 12 lists the types of PC cards in the Monitor Instrumentation electronics, the quantity of each type, and their monitor functions.

	Shutdown Cause	Possible Malfunctions	Trip Level	Final Mode
1)	High HE101 water electrolyzer temperature	Controller failure, sensor failure	1133 K(1580F)	Shutdown
2)	Low HE101 water electrolyzer temperature	Controller failure, sensor failure, heater failure	1113 K(1544F)	Standby
3)	High CE101 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure	1133 K(1580F)	Shutdown
· 4)	Low CE101 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure, heater failure	1113 K(1544F)	Standby
	High CE102 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure	1133K(1580F)	Shutdown
6)	Low CE102 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure, heater failure	1113 K(1544F)	Standby
7)	High CE103 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure	1133 K(1580F)	Shutdown
8)	Low CE103 CO <sub>2</sub> electrolyzer temperature	Controller failure, sensor failure, heater failure	1113 K(1544F)	Standby
9)	High COD101 CO disproportion- ator temperature	Controller failure, sensor failure	848 K(1067F)	Shutdown
10)	Low COD101 CO disproportion- ator temperature	Controller failure, sensor failure, heater failure	798 K(977F)	Standby
		·		continued-

	Shutdown Cause	Possible Malfunctions	Trip Level	Final Mode
11)	High COD102 CO disproportion- ator temperature	Controller failure, sensor failure	848 K(1067F)	Shutdown
12)	Low COD102 CO disproportion- ator temperature	Controller failure, sensor failure, heater failure	798 K(977F)	Standby
13)	High HSR101 H <sub>2</sub> separator temperature	Controller failure, sensor failure	693 K(788F)	Shutdown
14)	High HSR102 H <sub>2</sub> separator temperature	Controller failure, sensor failure	658 K(725F)	Shutdown
15)	High C101 control instru- mentation temperature	Controller failure, sensor failure	338 K(149F)	Standby
16)	Low FB101 flash boiler temperature	Controller failure, sensor failure, heater failure	383 K(230F)	Standby
17)	High drum voltage in HE101, CE101, CE102 or CE103	Electrolyzer drum failure	4.4 VDC	Standby
18)	High $\Delta P$ across CE101, CE102 and CE103	Blockage in electrolyzer module	$2.49 \times 10^3 \text{N/m}^2$ (10 in of H <sub>2</sub> 0)	Standby
19)	Low ΔP across CE101, CE102 and CE103	Leak in the electrolyzer module, low flow through the modules due to a system blockage	2.49 x 10 <sup>2</sup> N/m <sup>2</sup> (1 in of H <sub>2</sub> O)	
	·			continued-

48

49

	Shutdown Cause	Possible Malfunctions	Trip Level	Final Mode
20)	High recycle loop pressure	System blockage, build up of non-electrolyzable gas in the loop, electrolyzer malfunction, H <sub>2</sub> separator failure	1.21 x 10 <sup>4</sup> N/m <sup>2</sup> above ambient (1.75 Psig)	Standby
21)	Low recycle loop pressure	Leak in the system, controller failure, H <sub>2</sub> separator failure	$1.72 \times 10^3 \text{N/m}^2$ above ambient (0.25  Psig)	Standby
22)	High∆ P across COD101 when it is "on line"	Blockage in the CO disproportionator	TBD	Standby
23)	High $_{\Delta}$ P across COD102 when it is "on line"	Blockage in the CO dispro- portionator	TBD	Standby
24)	High HSR101 output pressure	H <sub>2</sub> separator failure, H <sub>2</sub> line blockage, ground support vacuum pump failure	$3.45 \times 10^3 \text{N/m}^2$ (0.5 Psia)	Standby
25)	Low drum voltage in HE101, CE101, CE102, or CE103	Electrolyzer drum failure	2.0 VDC	Standby

TABLE 11 SX-1 MONITORED PARAMETERS

_		<ul> <li>Type of Display</li> </ul>	Comments	SX-1 Ground Su Type of Display	Comments
1)	HE101 <sup>(a)</sup> water electrolyzer oven temperature			Digital panel meter temperature readout	From TS101 vicontrol instrumentation
2)	HE101 water electro- lyzer module temp- erature	Two sets of four level trend and fault indicators, one each for high and low temperature	From TS102	Digital panel meter temperature readout	From TS102 v monitor instance
		•		Thermocouple test points	From TS103 at TS104
3)	CE101 CO <sub>2</sub> electro- lyzer oven temper- ature			Digital panel meter temperature readout	From TS105 v control inst
4)	CE101 CO <sub>2</sub> electro- lyzer module temp- erature	Two sets of four level trend and fault indicators, one each for high and low temperature	From TS106	Digital panel meter temperature readout	From TS106 v monitor inst mentation
	er gen	and low competature		Thermocouple test points	From TS107 at TS108
5)	CE102 CO <sub>2</sub> electro- lyzer oven temp- erature	•		Digital panel meter temperature readout	From TS109 vicontrol instimentation
	CE102 CO <sub>2</sub> electro- lyzer module temp- erature	Two sets of four level trend and fault indicators, one each for high and low temperature	From TS110	Digital panel meter temperature readout	From TS110 vimonitor instrumentation

Monitored Parameter	SX-1 Trend and Fault Analysis Panel		SX-1 Ground Support Panel	
	Type of Display	Comments	Type of Display	Comment:
7) CE103 CO <sub>2</sub> electro- lyzer oven temp- erature			Digital panel meter temperature readout	From TS113 control in mentation
8) CE103 CO <sub>2</sub> electro- lyzer module temp- erature	Two sets of four level trend and fault indicators, one each for high and low temperature	From TS114	Digital panel meter temperature readout	From TS114 monitor in mentation
			Thermocouple test points	From TS115 TS116
9) COD101 CO disproportionator oven temperature			Digital panel meter temperature readout	From TS117 control in mentation
10) COD101 CO disproportionator internal temperature	Two sets of four level trend and fault indicators, one each for high and low temperature	From TS118	Digital panel meter temperature readout	From TS118 monitor in mentation
	might and for competators		Thermocouple test points	From TS119 TS120
11) COD 102 CO dispro- portionator oven temperature			Digital panel meter temperature readout	From TS121 control in mentation
2) COD102 CO disproportionator internal temperature	Two sets of four level trend and fault indicators, one each for	From TS122	Digital panel meter temperature readout	From TS122 monitor in mentation
	high and low temperature		Thermocouple test points	From TS123 TS124

Table 11 - continued

ameter	SX-1 Trend and Fault Analysis Panel		SX-1 Ground Support Panel	
	· Type of Display	Comments	Type of Display	Comments
ol in- on temp-	A set of four level trend and fault indicators for high temperature	From TS125		
separator rature			Digital panel meter temperature readout	From TS126 via control instra mentation
emper-	A set of four level trend and fault indicators for high temperature	From TS129	Digital panel meter temperature readout	From TS129 vi. monitor instr mentation
eparator rature			Digital panel meter temperature readout	From TS128 vi control instr mentation
eparator empera-	A set of four level trend and fault indicators for high temperature	From TS130	Digital panel meter temperature readout	From TS130 vi monitor instr mentation
boiler	A set of four level trend and fault indicators for low temperature	From TS127 via control instrumentation	Analog panel meter temperature readout	From TS127 vi control instr mentation
elect dividual es (8)	Two sets of four level trend and fault indicators, one each for high and low drum voltage. The eight individual drums are scanned by a multiplexer.	From voltage taps VS-101-1 through VS-101-8.	Analog panel meter voltage readouts for each drum	From voltage taps VS-101-1 through VS-101 8 via monitor instrumentation
	eparator	A set of four level trend and fault indicators for high temperature  deparator and fault indicators for high temperature  Two sets of four level trend and fault indicators for low temperature  delected dividual trend and fault indicators, one each for high and low drum voltage. The eight individual drums are scanned by a	Type of Display Comments  A set of four level trend and fault indicators for high temperature  Reparator adure  Reparator adure  Reparator adure  Reparator and fault indicators for high temperature  Reparator adure  Reparator and fault indicators for high temperature  Reparator adure  Reparator	* Type of Display Comments Type of Display  * Digital panel meter temperature readout  * Digital panel meter temperature readout  * Temperature readout  * Type of Display  * Temperature readout  * Type of Display  * Temperature readout  * Type of Display  * Digital panel meter temperature  * Temperature readout  * Temperature readout  * Temperature readout  * Temperature readout  * Type of Display  * Temperature readout  * Temperature readout  * T

Monitored Parameter		SX-1 Trend and Fault Analysis Panel		SX-1 Ground Support Panel	
		• . Type of Display	Comments	Type of Display	Comments
20)	CE101 CO <sub>2</sub> electro- lyzer individual drum voltages (8)	Two sets of four level trend and fault indicators, one each for high and low drum voltage. The eight individual drums are scanned by a multiplexer.		Analog panel meter voltage readouts for each drum	From voltage tap VS-102-1 through VS-102-8 via monitor instru- mentation
?1)	CE102 CO electro- lyzer individual drum voltages (8)	Two sets of four level trend and fault indicators, one each for high and low drum voltage.  The eight individual drums are scanned by a multiplexer.	VS-103-1 through	Analog panel meter voltage readouts for each drum	From voltage taps VS-103-1 through VS-103- 8 via monitor instrumentation
2)	CE103 CO <sub>2</sub> electro- lyzer individual drum voltages (8)	Two sets of four level trend and fault indicators, one each for high and low drum voltage. The eight individual drums are scanned by a multiplexer.	From voltage taps VS-104-1 through VS- 104-8	Analog panel meter voltage readouts for each drum	From voltage taps VS-1-4-1 through VS- 104-8 via mon- itor instru- mentation
3)	HE101 water electrolyzer module voltage			Digital panel meter voltage readout	From VS101 via control instrumentation
24)	CE101 CO <sub>2</sub> electro- lyzer module volt- age			Digital panel meter voltage readout	From VS102 via control instru- mentation
25)	CE102 CO <sub>2</sub> electro- lyzer module volt-			Digital panel meter voltage readout	From VS103 via control instrumentation

Monitored Parameter		SX-1 Trend and Fault Analysis Panel Type of Display Comments		Type of Display	SX-1 Ground Support Panel Type of Display Comments	
26)	CE103 CO <sub>2</sub> electro- lyzer module volt- age			Digital panel meter voltage readout	From VS104 vi control instr mentation	
27)	HE101 water electrolyzer module current			Digital panel meter current readout	From CS101 vi control instr mentation	
28)	CE101 CO <sub>2</sub> electro- lyzer module cur- rent		·	Digital panel meter current readout	From CS102 vi control instr mentation	
29)	CE102 CO <sub>2</sub> electro- lyzer module cur- rent			Digital panel meter current readout	From CS103 vi control instr mentation	
30)	CE103 CO <sub>2</sub> electro- lyzer module cur- rent			Digital panel meter current readout	From CS104 vi control instr mentation	
31)	ΔP across CE101 through CE103 CO <sub>2</sub> electrolyzers	Two sets of four level trend and fault indicators, one each for high and low $\Delta P$	From PS101	Analog panel meter ΔP readout	From PS101 vi monitor instr mentation	
	Recirculation loop pressure	Two sets of four level trend and fault indicators, one each for high and low pressure	From PS102	Analog panel meter pressure readout	From PS102 vi monitor instr mentation	
-	ΔP across COD101 CO disproportion- ator	A set of four level trend and fault indicators for high $\Delta P$	From PS103	Analog panel meter pressure readout	From PS103 vi monitor instr mentation	

Table 11 - continued

Monitored Parameter	SX-1 Trend and Fault Analysis Panel		SX-1 Ground-Support Panel		
	. Type of Display	Comments	Type of Display	Comments	
<ul><li>ΔP across COD102</li><li>CO disproportion- ator</li></ul>	A set of four level trend and fault indicators for high $\Delta P$	From PS104	Analog panel meter pressure readout	From PS104 via monitor instru mentation	
5) Vacuum pressure of HSR101 and HSR102 H <sub>2</sub> separators	A set of four level trend and fault indicators for high vacuum pressure	From PS105			
6) P101 bellows pump drive motor speed		·	Analog panel meter speed readout	From SS101 via control instru mentation	
		. •			
		•			

TABLE 12 MONITOR INSTRUMENTATION PRINTED CIRCUIT CARD LIST

Qty.	Card No.	Title	Monitor Function(s)
1	B2	Thermistor Temperature Monitor	High instrumentation temperature
14	В6	0 to 5 VDC Monitor	Low electrolyzer, disproportionator and flash boiler temperatures, high and low ${\rm CO}_2$ electrolyzer ${\rm \Delta P}$ , high and low recycle loop pressure, high disproportionator ${\rm \Delta P}$ and high ${\rm H}_2$ separator vacuum pressure.
8	В7	Voltage Level Monitor	High and low electrolyzer drum voltages
4	BC14	Multiplexer Switches	Scan of electrolyzer drum voltages
1	BC15	Multiplexer Timing	Scan of electrolyzer drum voltages
8	BC16	Thermocouple Tempera- ture Monitor	High electrolyzer, disproportionator and H <sub>2</sub> separator temperatures
1	I1	Logic Interface	Input/output interface

<sup>37</sup> Total Monitor Printed Circuit Cards

#### GROUND SUPPORT ACCESSORIES

Various items of support equipment are required to simulate the actual space-craft interfaces of the SX-1. These GSA, shown in Figure 16, are needed to compensate for the absence of spacecraft cabin resources (power, water, space vacuum and  $N_2$  purge) to synthesize the exhaust gas from the various  $CO_2$  collection subsystems over the operating ranges required during the subsystem parametric testing, and to monitor subsystem operation throughout the test program. Four distinct GSA were provided: (1) Ground Checkout Unit (GCU), (2) Fluid Supply Unit (FSU), (3) Space Vacuum Simulator (SVS), and (4) Gas Products Monitor (GPM).

#### Ground Checkout Unit

The GCU provides for the analog readout of parameters necessary to monitor the performance of the subsystem during the program test phase. Since the SX-1 does not require the GCU instrumentation to perform its intended function, the GCU has been designed only to read out important parametric test data. front panel of the GCU, shown in Figure 17 is called the Parametric Data Display Panel. It contains five digital panel meters which display Electrolyzer Module voltage, Electrolyzer Module current, Electrolyzer Module temperature, CO Disproportionator temperature and H, Separator temperature. Adjacent to the digital panel meters are thumbwheel switches which allow data from each of the various system components to be individually displayed. The GCU also contains 37 edge-type analog panel meters. Thirty-two of these meters are used to monitor individual electrolyzer drum voltages (eight drums in each of the four electrolyzer modules). The remaining five meters are used to monitor CO, Electrolyzer differential pressure, recycle loop pressure, CO Disproportionator differential pressure, Recycle Loop Bellows Pump speed and Water Feed Mechanism temperature.

Also provided on the Parametric Data Display Panel is a temperature output terminal and corresponding selector switch which provides thermocouple connectors to allow monitoring of the system's auxiliary temperature sensors. The auxiliary temperature sensors are mounted at various places in the Electrolyzer Modules and CO Disproportionators. Since these signals are not processed by the Control or Monitor Instrumentation, the sensor information must be monitored by an external instrument. The temperature selector shown on the GCU front panel chooses which sensor information is presented at the output connectors.

The final data display on the GCU is the subsystem's status summary. This display provides information summarizing the status (shutdown, alarm, warning, caution or normal) of the parameters monitored by the Monitor Instrumentation. An operator can quickly check on qualitative system operation by observing the system status summary display.

## Fluid Supply Unit

The FSU is designed to simulate the feed gas mixtures from any of the three  ${\rm CO}_2$  collection subsystems, the EDC, the molecular sieve and the steam desorbed




FIGURE 16 SX-1 GROUND SUPPORT ACCESSORIES




FIGURE 17 GROUND CHECKOUT UNIT PANEL

solid amine, which could interface with the SX-1. The unit consists of mass flow controllers, mass flowmeters, deionized water accumulator, a gas humidifier, pressure regulators and various sensors, fittings and tubing. A schematic of the FSU is presented in Figure 18. Hydrogen,  $N_2$ ,  $CO_2$  and  $O_2$  are supplied to the FSU where they are regulated to simulate the exhaust from any  $CO_2$  collection subsystem. Check valves in the  $H_2$  and  $O_2$  lines insure that no upstream mixing can occur in case of mechanical failure. The gases are mixed and humidified to a selected water vapor content and then flow through a moisture trap, dew point sensor and into the SX-1. The feed gas delivery pressure can be varied between 101 and 136 kN/m above ambient (0 and 5 psig).

Distilled water is supplied to the SX-1 Water Feed Mechanism by filling an accumulator and then pressurizing it with air. This allows the water to be delivered to the Water Feed Mechanism at a preset flow rate without entrapped air. Provisions have been included to allow for the refilling of both the feed gas humidifier and distilled water accumulator. The FSU supplies the SX-1 with 308 kN/m above ambient (30 psig) N<sub>2</sub> for startup, CDC replacement and shutdown. In addition, if the SX-1 experiences a total power failure, the FSU contains a battery-powered emergency purge unit which will supply N<sub>2</sub> to the subsystem for two minutes.

#### Space Vacuum Simulator

A SVS was designed to furnish the SX-1 with the vacuum normally encountered when the system is venting to space. The SVS consists of two mechanical type vacuum pumps, two vacuum gauges, and associated tubing and fittings. One pump maintains a vacuum on the  $\rm H_2$  Separator which remains constant and unaffected by pressure fluctuations during subsystem operation. The other pump is used to evacuate the CO Disproportionator prior to cartridge replacement. The CO Disproportionator is first evacuated then refilled with  $\rm N_2$ , thereby eliminating the possibility of toxic gases escaping during the maintenance activities.


#### Gas Products Monitor

The GPM allows the exhaust gases from the SX-1 to be monitored and sampled. The H<sub>2</sub> and O<sub>2</sub> exhaust lines from the Water Electrolyzer Module and the O<sub>2</sub> lines from the CO<sub>2</sub> Electrolyzer Modules are plumbed into the GPM so that they can either be vented or fed directly into a gas chromatograph for analysis; thereby allowing the product gases to be sampled without affecting the operation of the subsystem. Ports are also provided to sample the recycle loop gases at the CO Disproportionator, the CO Electrolyzer and H<sub>2</sub> Separator, and the CO Disproportionator vent gas. Provisions to monitor gas temperatures at these locations are also included. The feed gas humidifier and feed gas delivery temperatures in the FSU, the recycle loop samples and the CO Disproportionator vent temperatures can be displayed. Hydrogen and CO sensors were placed near the system to insure personnel and equipment safety.

#### PRODUCT ASSURANCE PROGRAM

The Product Assurance Program encompassed the activities associated with Quality Assurance, Reliability, Safety and Maintainability.

#### FIGURE 18 SX-1 FSU SCHEMATIC



### Quality Assurance

The Quality Assurance activities for the SX-1 consisted of the following:

- 1. Performance of receiving, in process and final inspections of all SX-1 components received and manufactured.
- 2. Participation in the design phase of the SX-1 program to insure the incorporation of Quality Assurance considerations in component and system design.
- 3. Assurance of configuration control by monitoring the Drawing and Change Control Procedures.
- 4. Monitor of all SX-1 testing.
- 5. Preparation and maintenance of system and component specifications.
- 6. Preparation of a failure reporting procedure which was to be utilized during the SX-1 Endurance Testing.

#### Reliability

The Reliability activities carried out during the SX-1 development program consisted of performing a Failure Mode Effects and Criticality Analysis (FMECA) and participation in component and system design to insure that concepts such as overdesign, derating and redundancy were incorporated.

For the FMECA that was performed on the SX-1 system, each component, as shown on the system schematic, was analyzed with regard to its failure modes, the failure effect on component/functional assembly, the failure effect on the system, the failure detection method, and crew action required. A criticality level was assigned to each failure mode as described below:

### Criticality

- I A single failure which could cause loss of personnel.
- IIa A single failure whereby the next associated failure could cause loss of personnel.
- A single failure whereby the next associated failure could cause return of one or more personnel to earth or loss of subsystem function(s) essential to continuation of space operations and scientific investigation.
- III A single failure which could not result in loss of primary or secondary mission objectives or adversely affect crew safety.

The analysis revealed that the SX-1 contains criticality IIa failure modes. These failure modes are the external leakage failure mode of all components which carry  $\rm H_2$  or CO. If these failure modes are allowed to persist, dangerous levels of  $\rm H_2$  or CO could be attained in the cabin atmosphere. The next associated failure which could cause loss of personnel would be the failure of a detector whose function would be to detect the leak and initiate system shutdown and  $\rm N_2$  purge. For flight applications, this hazard would be reduced by incorporating redundant  $\rm H_2$  and CO level detectors. An example of a FMECA is presented in Figure 19.

#### Safety

A major effort was made during the design phase of the SX-1 to include those safety features which would minimize danger to personnel. Consideration was given to the operational functions of the system and to all maintenance functions that must be performed. In addition, equipment protection features were incorporated in the safety design criteria to insure that off-design system operation would not result in damage to system components. Fail-safe characteristics, safety interlocks and system shutdown instrumentation were included in the system design to insure safety.

The safety design criteria utilized during the design, fabrication, assembly and testing of the SX-1 is divided into three sections: System Design Guidelines, Mechanical Design Guidelines, and Electrical Design Guidelines.

## System Design Guidelines

- 1. Personnel safety will not be compromised in meeting system performance requirements.
- 2. A single failure in one component will not cause successive failures in other components.
- 3. A single failure of any component will not expose personnel to the possibility of injury.
- 4. All hazardous failure modes that are identified in the FMECA will be eliminated by incorporation of safety interlocks, instrumentation and/or system shutdown.
- 5. The system will be designed so that all maintenance can be accomplished without hazard to personnel.
- 6. Service points for the fluids and gases involved will be designed with positive protection by location, connector size or type to prevent connection to incorrect fluid and gas service lines.
- 7. All components that require protective devices will be interconnected in such a way that failure of a single element will not fail both devices.

	Fe System			FAILURE MODE, EFFECTS & CRITICALITY ANALYSIS					REVISION LTR. DATE
TITLE	H <sub>2</sub> SEPARATOR	R, ITEM NO.	HSR101 and HS	SR102		□ SUBSYS		<u> </u>	MPONENT
PART NO.	RELIABILITY LOGIC NO.	Z	AME		FU	INCTIO11			
HSR- 101 N/A H <sub>2</sub> Separator To remove H <sub>2</sub> from the SX-1 feed gas and recycle loop gas.  HSR- 102									
a. coupl b. coupl c. d. leak, FAILUR a. perat will the s b. heate be ca c. d. e. FAILUR a. monit syste the e will high b. decre	E MODE AND CAL Control or more or electronic Control or more e or electronic Heater fails. Internal leak weld degrada  E EFFECT ON COM If the control ure signal with be no effect eparator would If the control ure no urrent, if used. The heater with It will be more Recycle loop E EFFECT ON SYS If the control or temperature m will lose in vent of the control ase, its H2  EE DETECTION ME	nitor temperic malfunctinitor temperic malfunctinitor temperic malfunctinitor temperic malfunctinitor malfunction malfunctinitor malfunctini malfun	ton.  rature sensor ton.  loop gases to ag tube ruptur  NCTIONAL ASSEA tls low the ir heater currer if the contro to heat withou ails high, the r sensor fails  r maintain the t to maintain admitted to 1  M: ils low, a sys If the monitor capability for erature sensor and the H <sub>2</sub> se ils high, the	fails his  o H <sub>2</sub> vent, re. (co  ABLY: Instrumenta int, if the ol sensor it any pro e control is high, an e separate H <sub>2</sub> vent the cabin  stem shute r temperate or high H r also fai eparator temperate ecrease as	caused be caused by caused	d by shown on page on receives sensor ls low (for shutentation ic system ature.  ensue in or fails or temper (double damaged lee H2 sepurally a sepura	ving a fails double down. will do m shuto failure failure failure by exponents arator ubsyste	low fa:	III III v tem- there ilure) ease n will  by the n the d, in there re to
ı	b, c. Redund d. Recycl	ant temperat	separator exh	aust pres	sure s <b>e</b> ns	or.			
	ACTION REQUIRE b, c, d, e.		of separator	•			TIME REQU	۱.۰	TIME AVAIL. N/A

FIGURE 19 FAILURE MODE EFFECTS AND CRITICALITY ANALYSIS

(a) After system cool-down

Figure 19 - continued

1	Cife Syste	ems, Inc.	NUMBER		REVISION LETTER			PAGE 2		
	CLEVELAND,									2
PART NO.	RELIABILITY LOGIC NO.	NAMI			FUN	CTIC	)11			
HSR- 101 and HSR- 102	N/A	H <sub>2</sub> Separat	or	To remove H <sub>2</sub> recycle loop g		the	s SX-	·1 fe	eed g	as and
FAILUR	E MODE AND CA	USE:				-			CR	ITICALITY
	External leak	age.  MPONENT/FUNCT	IONAL ASSEM	ABLY:					e.	IIa
senso c. decre d. e.	caused by high rails high, Temperature of ase. Eventua Loss of feed The recycle 1	a subsystem s f H <sub>2</sub> separator l system shutd gas and recycl oop gases (H <sub>2</sub> ,	hutdown work will decre own will oce e loop pres CO, CO,	will occur. Is ald occur. ease, H <sub>2</sub> remova ccur because of ssure, a low prowould be admitted. H <sub>2</sub> level detections	l car hig essu ed t	paci h re re s o th	ity v ecyc: shuto ne ca	vill le lo lown abin	also oop p woul	oressure.
FAILUR	RE DETECTION ME	THOD:								
CREW	ACTION REQUIRE	D:							ME QD.	TIME AVAIL.

- 8. Mounting and connections will be designed so that the component or its connections cannot be inadvertently reversed.
- 9. Manual override techniques will be provided for critical automatic functions to permit safe operation to shut down during an emergency.
- 10. Since the system will contain hazardous and toxic gases (H<sub>2</sub> and CO) a N<sub>2</sub> purge will be incorporated so that a system purge can be performed prior to startup, after shutdown and prior to performing maintenance activities.
- 11. Hydrogen and CO gas monitors will be installed near the system in strategic locations to sense for leakage of these hazardous gases. The units will alarm and the system will be shut down when H<sub>2</sub> and/or CO concentration reaches dangerous levels.
- 12. The system will be designed so that components that are susceptible to pressure damage are protected. Protection can be by incorporation of pressure relief valves or system shutdown followed by venting and  $\rm N_2$  purge.
- 13. Overtemperature protection by automatic shutdown will be incorporated for those components that are susceptible to high temperature damage.
- 14. A caution and warning system will be incorporated into the instrumentation design to provide an indication prior to occurrence of a dangerous situation. This will consist of Life Systems' Trend and Fault Analysis instrumentation.
- 15. All known possibilities of human error in system operation will be eliminated. Accidental activation of system components of the system itself, which might cause damage, will be given special consideration to minimize or eliminate the possibility of accidental actuation. Noncritical controls will be located in areas where accidental actuation is improbable, critical controls will be protected by a physical guard. Where sequence of operations is critical, an interlock system which prevents out-of-order manipulation of controls will be used. All such sequential operations will be designed so that operation is automatic upon issuing the command to start up, shut down or to change operating mode. In an override condition, labels and warnings will be posted to prevent out-of-sequence operation.
- 16. Human engineering consideration will be given to both operation and maintenance of the SX-1. Special attention will be given to the handling provisions, visual displays, illumination, and labels. The company's safety program includes analysis to determine where human error during operation and maintenance could cause a safety hazard. This information will be incorporated into the final design to minimize the chance of human error causing a safety hazard.

- 17. Provisions will be included in the system design to insure that the product 0<sub>2</sub> gas meets NASA purity requirements. Product 0<sub>2</sub> purity will be monitored throughout system testing.
- 18. The automatic system shutdowns that are projected for inclusion in the design of the SX-1 are listed in Table 10.

## Mechanical Design Guidelines

- 1. All high temperature components will be insulated so that the surface temperature during operation is less than 323K (120F). In the event this is not practical, then warning signs and a protective standoff will be incorporated to protect personnel.
- 2. Carbon formation in the recycle loop will be prevented by screening components for unacceptable materials and replacing materials where required. Electroless nickel plated stainless steel, Inconel, Monel and copper are materials which will not catalyze the carbon formation reaction and will be acceptable for use in the recycle loop.
- 3. All moving parts will be shielded to prevent accidental contact with personnel.
- 4. Application of factors of safety typical for aerospace hardware will be incorporated into the design of structural components and parts.
- 5. Sharp edges and corners will be eliminated or will be adequately covered with a protective cushion to prevent injuries.
- 6. In order to avoid fatigue failures, the following guidelines will be adhered to:
  - a. Parts will be designed such that residual stress and surface defects are minimized.
  - b. Fillet radii will be made as generous as possible.
  - c. Sharp edges will be broken.
  - d. Corrosion protection of metals will be considered to avoid corrosion fatigue problems.
- 7. A procedure for describing the safe handling of the hazardous gases in the system will be prepared and implemented during the operation of the system and testing of the various components.

# Electrical Design Guidelines

1. All electrical equipment will be enclosed in vented containers.

- 2. The power supplies utilized in the system will be designed to accept peak and transients which may occur.
- 3. Circuit breakers will be incorporated in the ground support to protect electrical equipment from unexpected high current. All DC supplies in the system will have current limits to prevent component damage.
- 4. All electronic enclosures will be grounded.
- 5. Electrical equipment which could contact personnel or other conductive equipment that could contact personnel will be equipped with current limiting devices which prevents an injurious current from passing through the human body. Limiting currents will be as defined in NASA CR-1205, "Compendium of Human Responses to the Aerospace Environment," Vol. 1, Section 5.
- 6. Electrical connectors, plugs and receptacles will be positively keyed to prevent incorrect mating with other accessible connectors, plugs, or receptacles.
- 7. Wherever practical, the "hot" (live) electrical connectors will be the (female) socket.
- 8. Electrical circuits will not be routed through adjacent pins of an electrical connector if a short between them will constitute a failure that could cause a serious disaster.
- 9. Warning labels will be provided on all access panels leading to high voltages.

## Maintainability

The Maintainability features designed and incorporated into the SX-1 follow:

- 1. The SX-1 components were overdesigned where possible to preclude failure of components resulting from operation at or near their maximum operational tolerance.
- 2. Automatic control was incorporated into the SX-1 to vary CO<sub>2</sub> Electrolyzer Module current to compensate for variable CO<sub>2</sub> feed rates and to provide the controlled sequencing of components when changing from one operating mode to another.
- 3. Performance trend and fault analysis instrumentation was included in the SX-1 to provide advance warning of out-of-specification operating conditions. This serves to avoid system shutdowns by alerting test engineers of problems before they degrade system performance.

- 4. Equipment protection features were included in the system design to increase the operating life of the SX-1. These include the incorporation of safety shutdowns for out-of-tolerance temperatures and pressures.
- 5. The only identified servicing are the activities associated with the Reactor Change operating mode and monitoring of the System Status Summary on the Parametric Data Display Panel. The system was designed such that the Reactor Changeover does not interrupt system operation.
- 6. The SX-1 was packaged for ease of accessibility to all components with the exception of the Electrolyzer Module and CO Disproportionator heaters. A failure of one of these heaters would involve a significant maintenance activity involving the removal and replacement of insulation.
- 7. A Standby Mode was incorporated in the design to prevent unnecessary temperature cycling of the SX-1 components, in particular, the Electrolyzer Modules. The Standby Mode is similar to the Shutdown Mode except all system heaters remain on and the temperatures of all components are controlled at their normal operation set points.

#### PROGRAM TESTING

The SX-1 testing activity was to consist of a five part effort:

- 1. Component Checkout and Calibration Tests
- 2. Major component DVT
- 3. SX-1 Checkout and Shakedown Tests
- 4. SX-1 Parametric Tests
- 5. SX-1 Endurance Tests

Due to the occurrence of electrolyzer drum leakage, the DVT of the Electrolyzer Modules and the system checkout, shakedown, parametric and endurance testing were not performed. The component DVTs that were performed are discussed below.

### Electrolyzer Drum Leak Tests

The Electrolyzer Drums used in the electrolyzer modules were fabricated, assembled and tested under Contract NAS2-6412. They were to be made available as Government-Furnished Property (GFP) for assembly into the SX-1 Electrolyzer Modules. Twenty-nine electrolyzer drums were reported as acceptable at the conclusion of NAS2-6412. Upon receipt of the GFP electrolyzer drums, they were leak-tested using a  $\Delta t/\Delta P$  leak test procedure. This procedure involves pressurizing the electrolyzer drums to 15.2 cm (6.0 in) of water, isolating the drum being tested and monitoring the time required for the pressure inside the drum to drop from 15.2 cm (6.0 in) of water to 12.7 cm (5.0 in). Electrolyzer drums taking less than two minutes for the pressure to decrease from 15.2 cm to 12.7 cm (6.0 to 5.0 in) of water are rejected. The electrolyzer

drums are baked at 423K (302F) prior to the test to insure that condensation is removed from any microporosity that might be present. If the moisture is not removed, false high  $\Delta t/\Delta P$  data can be obtained. The results of the  $\Delta t/\Delta P$  test are presented in Table 13. Thirty-one drums were tested: 6 were acceptable, 2 were marginally acceptable and 23 did not meet the requirements of the  $\Delta t/\Delta P$  test. Since the subject Electrolyzer Drums were previously tested at the conclusion of NAS2-6412 (approximately 28 months prior to the test reported here), it appears that either the electrolyzer drum seals are subject to degradation with time, or at some time during their storage, since the conclusion of NAS2-6412, they were inadvertently exposed to an excessive thermal gradient which deteriorated the precious metal/ceramic seals.

Attempts were made to reseal the electrolyzer drums by placing the drums in a resealing fixture and then heating them to the brazing temperature, 1353K (1976F), at a rate not exceeding 3K (5.4F) per minute. Only five of the leaky Electrolyzer Drums resealed.

It was postulated that if the seal failure was at a metal-to-metal joint, then the reseal procedure would be successful. However, if the seal failure was at a precious metal-to-ceramic joint, the reseal furnace run would do no good as the molten gold braze material would not wet the ceramic.

## Hydrogen Separator DVT

The H<sub>2</sub> Separators are used within the SX-1 recycle loop and the feed gas line to remove excess H<sub>2</sub> from the respective gas flows. A picture of one of the H<sub>2</sub> Separators is shown in Figure 9. A DVT was performed on the H<sub>2</sub> Separators which verified that both separators were leak-tight and that the performance of each separator exceeded the design requirement by more than 25%. The design requirement is a H<sub>2</sub> separation rate of 0.322 cm /s (0.68 x  $10^{-3}$  scfm) when operating at 645K (702F). Summary data is provided in Table 14.

# CO Disproportionator DVT

The CO Disproportionator is required in the SX-1 to convert the CO formed by the CO<sub>2</sub> Electrolyzer Modules into carbon and CO<sub>2</sub> for eventual recycling into the Electrolyzer Modules. The CO Disproportionator is shown in Figure 7. It was determined during the DVT of the CO Disproportionator that carbon was formed in areas other than the CDC. That is, disproportionation was taking place within the inlet tube and the inlet chamber of the CO Disproportionator prior to full disproportionation within the CDC assembly as planned. These areas had been electroless nickel plated to prevent carbon formation as reported previously in the description of the CO Disproportionator. As indicated, the electroless nickel was selected based on results reported in the literature in which this coating was used as a protective coating for preventing carbon formation during the Bosch reaction, which is:

$$CO_2 + 2H_2 = 2H_2O + C$$
 (9)

TABLE 13 ELECTROLYZER DRUM  $\Delta t/\Delta P$  TEST RESULTS

Drum No.	Initial $\Delta t/\Delta P$ Test Result (a)	Δt/ΔP Test After 423K (302F) Bake (a)	Disposition (b)
F-285	< 10 sec		
-297	< 10 sec		
-288	< 10 sec		
-287	>120 sec		
	(2 min)	81 sec	Marginal
-278	< 10 sec		
-279	< 10 sec		
-271	< 10 sec		
-292	< 10 sec		
-291	>120 sec	>120 sec	
	(2 min)	(2 min)	Acceptable
-302	>120 sec	>120 sec	
	(2 min)	(2 min)	Marginal
-277R	< 10 sec		
-283	< 10 sec		
-265	< 10 sec		
-298	< 10 sec		
-26 <b>9</b> Z	< 10 sec		
-303	< 10 sec		
-307	>120 sec		
	(2 min)	30 sec	
-286	>120 sec	>120 sec	
	(2 min)	(2 min)	Acceptable
-264	< 10 sec		
-308	>120 sec	>120 sec	
	(2 min)	(2 min)	Acceptable Acceptable
-289	< 10 sec		
-293	>120 sec	>120 sec	
	(2 min)	(2 min)	Acceptable
-284	< 10 sec		
-282	>120 sec	>120 sec	
	(2 min)	(2 min)	Acceptable
-295	< 10 sec		
-301	< 10 sec		
-294	< 10 sec		
-266	< 10 sec		
-268	< 10 sec		
-281	< 10 sec	. 100	
-273	>120 sec	>120 sec	A = = = = 1-1
	(2 min)	(2 min)	Acceptable

<sup>(</sup>a) Time for pressure inside drum to drop from 15.2 cm (6 in) water to 12.7 cm (5 in) water.

<sup>(</sup>b) All those not marked are unacceptable.

TABLE 14A HYDROGEN SEPARATOR TEST RESULTS SUMMARY (METRIC UNITS)

	Point	Module No.	Module Temp., K	Product H <sub>2</sub> Vacuum, mm Hg	H Separator Feed Gas Flow, cm <sup>3</sup> /s	H Separator Exit Gas Flow, cm <sup>3</sup> /s	H <sub>2</sub> Removal Rate, cm <sup>3</sup> /s	% Overcapacity (a)
	1	1	645-650	0.50	45.89	45.32	0.56	75
	2	1	645-650	0.50	45.80	45.32	0.52	62
	3	1.	655-661	0.54	45.87	45.16	0.68	112
	4	1	655-661	0.54	45.88	45.10	0.72	125
	5	1	665-678	0.55	45.92	45.20	0.69	115
	6	1	665-678	0.55	45.84	45.20	0.65	100
	7	1	617-625	0.38	48.32	47.76	0.49	53
	8	1	611-617	0.38	48.23	47.60	0.53	65
72	9	2	645-650	NA	45.89	45.48	0.41	28
	10	2	645-650	0.35	45.55	45.10	0.42	31
	11	2	645-650	0.35	45.57	45.15	0.41	28
	12	2	665-672	NA	49.97	49.30	0.67	109
	13	2	665-678	NA	50.17	49.35	0.82	156
	14	2	665-672	0.33	51.81	51.20	0.50	56
	15	2	665-672	0.33	51.73	51.12	0.50	56

<sup>(</sup>a) % Overcapacity =  $\frac{\text{H}_2 \text{ Removal Rate - Design H}_2 \text{ Removal Rate } (0.322 \text{ cm}^3/\text{s})}{\text{Design H}_2 \text{ Removal }^2 \text{Rate } (0.322 \text{ cm}^3/\text{s})} \times 100$ 

Life Systems, Inc

TABLE 14B HYDROGEN SEPARATOR TEST RESULTS SUMMARY (ENGLIGH UNITS)

Dat	a Point No.	Module No.	Module Temp., F	Product H <sub>2</sub> Vacuum, In Water	H <sub>2</sub> Separator Feed Gas Scfm x 10 <sup>2</sup>	H <sub>2</sub> Separator Exit Gas Scfm x 10 <sup>2</sup>	H <sub>2</sub> Removal Rate, Scfm x 10 <sup>3</sup>	% Overcapacity (a)
	1	1	700-710	0.268	9.723	9.600	1.195	75
	2	1	700-710	0.268	9.704	9.601	1.098	62
	3	1	720-730	0.289	9.718	9.569	1.439	112
	4	1	720-730	0.289	9.721	9.554	1.526	125
	5	1	740-760	0.294	9.729	9.576	1.470	115
	6	1	740-760	0.294	9.711	9.575	1.383	100
	7	1	650-665	0.203	10.237	10.119	1.034	53
73	8	1	640-650	0.203	10.219	10.085	1.113	65
•	9	2	700-710	NA	9.722	9.636	0.855	28
	10	2	700-710	0.187	9.650	9.555	0.886	31
	11	2	700-710	0.187	9.654	9.565	0.856	28
	12	2	740-750	NA	10.587	10.445	1.423	109
	13	2	740-760	NA	10.629	10.455	1.741	156
	14	2	740-750	0.177	10.977	10.846	1.065	56
	15	2	740-750	0.177	10.959	10.830	1.054	56

<sup>(</sup>a) % Overcapacity =  $\frac{\text{H}_2}{\text{Design H}_2} \frac{\text{Removal Rate - Design H}_2 \cdot \text{Removal Rate (0.68 x 10}^{-3} \cdot \text{cfm})}{\text{Rate (0.68 x 10}^{-3} \cdot \text{cfm})} \times 100$ 

Since the reaction mechanism of the Bosch and CO Disproportionator reactors are different, a material that retards carbon formation for one reactor may not for the other. However, it was later established that researchers working with Bosch reactors were also experiencing carbon formation on electroless nickel surfaces. The problem was attributed to variations in plating parameters that were difficult to control.

It was decided that a redesign or a material study would not be implemented due to the following two reasons: (1) the problem could be adequately handled by manual removal of carbon during the required carbon change cycles and (2) work was being done by other NASA contractors on material studies relating to the Bosch process and other carbon reduction processes. Thus it was felt that in the SX-1 program, carbon formation on the electroless nickel was not a problem that required immediate attention.

As shown in Figure 20, the conversion efficiency at an inlet gas flow rate of 3080 sccm (0.1088 scfm) ranged between 40 and 45% over a temperature range of 773 to 843K (932 to 1058F). This exceeded the reactor conversion efficiency design goal of 36% which was previously demonstrated. Data obtained during testing of the CO Disproportionator for integrated operational testing is provided in Table 15.

### Water Feed Mechanism DVT

The Water Feed Mechanism is used in the SX-1 to supply a constant flow of super-heated steam to the Water Electrolyzer Module. The steam is required as a source of additional 0, to make up the difference between the 0, available from CO, and that metabolically required by a man. A photo of the Water Feed Mechanism test stand is shown in Figure 21. As was noted in the Fourth Quarterly Report, 21 problems were incurred which resulted in certain design changes in the Water Feed Mechanism. The design changes were required to correct the effect of off-gassing in a 1 g environment to provide for a testing capability on the ground. Bubbles collected on the water side of the Water Feed Mechanism, thereby affecting the heat transfer area and causing erratic flow fluctuations. With the design changes and the orientation where the water side of the Water Feed Mechanism is pointed vertically up toward the water to steam orifice, the gas that is formed during normal operation is ejected through the orifice and out into the steam line. In this orientation, it causes no problems to the overall system operation. The temperature gradients and flow fluctuations that were being caused by erratic flow or expulsion of the accumulated gas no longer existed, and thus, a more stable system operation was achieved.

The DVT was completed after the modifications. All the steam flow rate data collected for the DVT were within the Water Feed Mechanism design range of 2.85 to  $5.70 \times 10^{-6}$  kg/s (0.544 to 1.09 lb/day). Long term data was consistent as evidenced by Figure 22 which is a plot of Water Feed Mechanism steam flow rate versus time.




FIGURE 20 CO DISPROPORTIONATOR CONVERSION EFFICIENCY VERSUS TEMPERATURE

TABLE 15A CO DISPROPORTIONATOR TEST RESULTS (METRIC UNITS)

	Temperatures, K						Conversion Efficiency Data					
Ī	ntern	al	Ex	terna	1	Exhaust	Exhaust Flow	Inlet Flow	% CO In	Conversion	Pressure Drop	
TC1	TC2	TC3	TC4	TC5	TC6	TC7	Rate, Sccm	Rate, Sccm	Exhaust	Efficiency, %	Across COD, N/m <sup>2</sup>	
								**************************************			,	
293	293	293	293	293	293	293				(a)		
775	803	800	577	833	633		2910	3080		43 <sup>(a)</sup>	0	
788	811	805	575	833	648	713	2730	3080		43	49.82	
807	833	825	577	855	672	738	2730	3080		43	49.82	
803	843	835	604	853	674	736	2730	8030		43	49.82	
802	831	824	591	843	658	736	2730	3080		43	49.82	
773	838	831	590	853	676	739	2750	3080		40.4	74.73	
799	833	826	584	853	676	739	2750	3080	35.7	50	74.73	
800	831	833	583	851	676	733	2780	3080		37	124.55	
804	839	833	584	852	698	743	2860	3080		27	174.37	
Exha	ust V	ent P	lugge	d Wit	h Ice	At Appro	ximately 2:00 A	M, 12/18/74			!	
737	837	829	583		693		2750	3080		40.4	1295.32	
745	826	828	583	843	692	734	2780	3080			1494.6	
Shut	down											
Exte	rnal	Therm	ial Co	uples	(TC4	-TC6) Mov	red					
	t Hea			•	•							
840	837	791	603	793	771	743	2650	3080			24.91	
Syst	em Ha	s Les	s Tha	.n 5%	Nitro	gen Remai	.ning					
773	849		(b)	793	790	791	2650	3080	35	41.4	24.91	
780	848	863		793	789	792	2630	2950	35	41.4	24.91	
Adju	st to	Lowe	r Flo	w and	High	Temperat	ure					
784	850	865		774	781	788	2325	2640	33.1	45.3	24.91	
747	826	814		778	795	765	2380	2670	35.1	41.2	24.91	
750	837	833		775	772	758	2380	2660	35.8	39.8	24.91	
768	831	852		788	777	775					24.91	
Adju	st F1	ow To	)			3500 Scc	em .					
789	846	841		783	775	778	3300	3670	36.6	38.4	24.91	

<sup>(</sup>a) Determined from inlet/exhaust flow rate

<sup>(</sup>b) TC4 failed

Table 15A - continued

		Temp	perat	ures,	K			Conve	rsion Effic	iency Data	
Ī	ntern	al	Ex	terna	1	Exhaust	Exhaust Flow	Inlet Flow	% CO In	Conversion	Pressure Drop
TC1	TC2	TC3	TC4	TC5	TC6	TC7	Rate, Sccm	Rate, Sccm	Exhaust	Efficiency, %	Accross COD, N/m <sup>2</sup>
768	841	843		783	773	781	3300	3670	36.9	37.8	24.91
778	837	850		783	775	783	3300	3670	36.7	38.2	24.91
			Appr			700 Sccm		30,0	331,	00,1	21.31
		Recyc									
	823			773		759	2750	3060	36.6	38.4	24.91
733	790	770		753	736	713	2750	3040	37.8	36.0	24.91
698	773	759		768	751	698	2750	3070	35.8	39.8	24.91
690	780	773		773	753	695	2780	3110	35.5	40.6	24.91
673	770	761		768	741	693	2750	3100	34.3	42.9	24.91
678	785	778		773	755	693	2750	3090	<b>35.</b> 2	41.1	24.91
693	782	773		773	751	693			34	43.4	24.91
Adju	st Flo	ov To	Appr	oxima	tely	750 Sccm					· · · · · ·
Adju	st To	Recyc	cle L	oop F	low R	ate					
727	775			773	745	689	2610	2950	34.2	43.1	49.82
712	772			773	737	690	2650	3000	33.7	44	49.82
						ed In Sta	ndby Mode				
•		as Flo	ow Re								
	774				753		2630	2960	34.7	42	124.55
702				775	746		2630	2970	34.2	43.1	124.55
_			_			ed In Sta	ndby Mode				
•		oop Ga	as Fl								
	791			783	755	698	2630	2980	33.3	44.8	149.46
	845			785	775		2680	2970	37.6	36.6	149.46
						ed In Sta	ndby Mode				
-		oop Ga	as Fl								
	801			811	768	705	2650	2980	35	41.4	1569.33
	791			803		706	2650	2980	34.6	42.3	1619.15
_			_			ed in Sta	ndby Mode				
		oop Ga	is Flo								
	849		_		783						2466.09
			as Coi	nposi	tion	Changed t	o 19.6% Hydrogen	n, 8.04% CO			
Test	Stop	ped									

TABLE 15B CO DISPROPORTIONATOR TEST RESULTS (ENGLISH UNITS)

		Tem	perat	ures,	F		Conversion Efficiency Data					
	Interr			terna		Exhaust	Exhaust Flow	Inlet Flow		Conversion	Pressure Drop	
TC1		TC3	TC4	TC5	TC6	TC7	Rate, Ft <sup>3</sup> /Min	Rate, Ft <sup>3</sup> /Min	Exhaust	Efficiency,%	Across COD, In Wate	
Amb		Amb	Amb	Amb	Amb	Amb				<del></del>		
936		981		1040	680	AllO	0.1028	0.1088		43	0	
	1000	990		1040	707	824	0.1028	0.1088		43	0.2	
	1040			1080	750	869	0.0964	0.1088		43	0.2	
	1058			1076	754	865	0.0964	0.1088		43	0.2	
	1036			1058	743	865	0.0964	0.1088		43	0.2	
	1030			1076	757	871	0.0971	0.1088		40.4	0.3	
	1045			1076	757	871	0.0971	0.1088	35.7	40	0.3	
	1036			1072	757	860	0.0982	0.1088		37	0.5	
	1051			1074	797	878	0.0946	0.1088		27	0.7	
							ximately 2:00 AM		1975			
		1033			788	Fr	0.0971	0.1088		40.4	5.2	
		1031			786	862	0.0982	0.1088			6.0	
	t Down											
			al Co	ouples	(TC4	-TC6) Mov	red.					
	rt Hea			•	•	-						
			626	908	928	878	0.0936	0.1088			0.1	
Sys	tem ha	as les	s tha	an 5%	Nitro	gen Remai	ning.					
932	1069	1094	(b)	968	963	964	0.0936	0.1088	35	41.4	0.1	
945	1067	1094		968	961	966	0.0929	0.1042	35	41.4	0.1	
Adj	ust to	o Lowe	r Flo	ow and	l High	Temperat						
952	1071	1098		934	946	959	0.0821	0.0932	33.1	45.3	0.1	
	1027			941	972	918	0.0840	0.0943	35.1	41.2	0.1	
	1047			936	930	905	0.0840	0.0939	35.8	39.8	0.1	
923	1036	1074		959	939	936	7				0.1	
Adj	ust F	low to	App:	roxima	itely	0.1236 Ft	3/Min.			<b>50</b> 4	0.1	
961	1063	1054		950	936	941	0.1165	0.1298	36.6	38.4	0.1	
		1058		950	932	946	0.1165	0.1298	36.9	37.8	0.1	
941	1047	1071		950	936	950	0.1165	0.1298	36.7	38.2	0.1	
Adj	ust F	low to	App	roxima	itely	0.0247 Ft	cy/Min.					

<sup>(</sup>a) Determined from inlet/exhaust flow rate.

<sup>(</sup>b) TC4 failed.

Table 15B - continued

		ratures, F	·			Conversi	on Effici	ency Data	
Inte	ernal	Externa	1	Exhaust	Exhaust Flow	Inlet Flow	% CO In	Conversion	Pressure Drop
TC1 T	TC2 TC3	TC4 TC5	TC6	TC7	Rate, Ft <sup>3</sup> /Min	Rate, Ft <sup>3</sup> /Min	Exhaust	Efficiency,%	Across COD, In Water
Adjust	to Recy	cle Loop F	low R	ate.					
	022 1018	932	937	907	0.0971	0.1081	36.6	38.4	0.1
860 9	963 927	896	865	824	0.0971	0.1074	37.8	36.0	0.1
797 9	932 907	923	892	497	0.0971	0.1084	35.8	39.8	0.1
783 9	945 932	932	896	422	0.0981	0.1098	35.5	40, 6	0.1
752 9	927 910	923	874	788	0.0971	0.1095	34.3	42.9	0.1
761 9	954 941	932	900	788	0.0971	0.1091	35.2	41.4	0.1
788 9	948 932	932	892	788			34.0	43.4	0.1
Adjust	: Flow to	Approxima	tely	0.0265 Ft	<sup>3</sup> /Min.				1
		cle Loop F							1
849 9	936 907	932	882	781	0.0922	0.1042	34.2	43.1	0.2
822 9	905	932	867	783	0.0936	0.1059	33.7	44.0	0.2
Purged	l With Ni	trogen and	Plac	ed in Sta	ndby Mode.				
Recyc1	e Gas Flo	ow Resumed	. •		·				
781 9	934 937	968	896	788	0.0929	0.1045	34.7	42.0	0.5
804 9	928	936	883	788	0.0929	0.1049	34.2	43.1	0.5
Purged	l With Nit	trogen and	Plac	ed in Sta	ndby Mode.				
Recyc1	le Loop Ga	as Flow Re	sumed	•	•				l l
	964 910	950	900	797	0.0929	0.1052	33.3	44.8	0.6
820 10	062 1071	954	936	925	0.0946	0.1049	37.6	36.6	0.6
Purged	l With Ni	trogen and	Plac	ed in Sta	ndby Mode.				
Recyc1	le Loop Ga	as Flow Re	sumed	. •					
813 9	966	1000			0.0936	0.1052	35.0	41.4	6.3
824 9	964 939	986	925	811	0.0936	0.1052	34.6	42.3	6.5
Purged	l With Nit	trogen and	Plac	ed in Sta	ndby Mode.				
Recyc1	le Loop Ga	as Flow Re							
793 10	069 1076	964	950	943					9.9
		as Composi	tion	Changed to	o 19.6% Hydrogen	, 8.04% CO.			ı
Test S	Stopped	_		- <del>-</del>					10.9
									10.9




FIGURE 21 WATER FEED MECHANISM TEST STAND




FIGURE 22 WATER FEED MECHANISM FLOW RATE VERSUS TIME

## Control and Monitor Instrumentation DVT

The Control and Monitor Instrumentation is used in the SX-1 for control of all heaters, current controls and sequence controls and to monitor the trends of the system, respectively.

All control PC cards were individually calibrated and checked out on the Life Systems' special PC card tester. The list of Control Instrumentation PC cards was presented in Table 9. The control points were set by using simulated input signals. Next, a wiring continuity check on the Control Instrumentation backplane and a check of all Control Instrumentation power supplies was performed. Printed circuit cards were then inserted into the Control Instrumentation package, one function at a time, to determine that the particular function, independent of the remainder of the Control Instrumentation, was operating properly. The CO Disproportionator temperature control cards were set up to functionally operate the proper heaters. The resulting control characteristics of temperature versus time can be found in Figure 23. In a like manner, the electrolyzer module temperature control cards and temperature ramp cards were checked out and the results are presented in Figure 24. The purpose of the temperature ramp card is to ensure that the electrolyzer module heat-up rate is 3K (5.4F)/min. This is necessary to prevent damage to the ceramic parts of the electrolyzer drums and modules.

The main sequence cards were checked out on the Life Systems special PC card tester. The memory addresses were simulated with input switches and the memory outputs were connected to light-emitting diodes (LEDs). A pulse generator was used to step through the sequence one state at a time. For a given memory address, the output LEDs were checked for proper ones and zeros according to the required bit pattern. The sequence was checked out for proper operation of all devices in the Purge, Normal, Standby, Reactor Change and Shutdown Modes.

The last step of the Control Instrumentation DVT included checking out the Control Instrumentation/SX-1 interface, including all sensor inputs, actuators, heater outputs and interfaces with the GSA and Monitor Instrumentation.

A wiring continuity check was performed on the Monitor Instrumentation backplane. All monitor PC cards were individually calibrated and checked out on the Life Systems' special PC card tester. A list of the Monitor Instrumentation PC cards was presented in Table 12. The Monitor Instrumentation trip points were set on the individual cards in accordance with Table 16. This was done by applying simulated input signals and adjusting the appropriate potentiometers accordingly. All normal, caution, warning and alarm indicaters were checked for proper operation at the levels indicated in Table 16. Table 17 lists the value in engineering limits that correspond to the voltage trip points. The final step in the Monitor Instrumentation test included checking out the integration of the Monitor Instrumentation with the remainder of the SX-1 system.




FIGURE 23 CO DISPROPORTIONATOR TEMPERATURE CONTROL CHARACTERISTICS




FIGURE 24 ELECTROLYZER MODULE TEMPERATURE CONTROL CHARACTERISTICS

TABLE 16 MONITOR INSTRUMENTATION VOLTAGE TRIP POINTS

Carbon Dioxide Electrolyzer	Caution	Warning	Alarm
Module 1 High Voltage Low Voltage High Temperature Low Temperature	3.600	4.000	4.400
	3.000	2.500	2.000
	4.300	4.350	4.375
	4.200	4.150	4.125
Module 2 High Voltage Low Voltage High Temperature Low Temperature	3.600	4.000	4.400
	3.000	2.500	2.000
	4.300	4.350	4.375
	4.200	4.150	4.125
Module 3 High Voltage Low Voltage High Temperature Low Temperature	3.600	4.000	4.400
	3.000	2.500	2.000
	4.300	4.350	4.375
	4.200	4.150	4.125
High ΔP	1.250	2.000	2.500
Low ΔP	0.500	0.475	0.125
Water Electrolyzer			
High Voltage Low Voltage High Temperature Low Temperature Low Water Feed Temperature	3.600	4.000	4.400
	3.000	2.500	2.000
	4.300	4.350	4.375
	4.200	4.150	4.125
	0.877	0.700	0.550
CO Disproportionator			
Reactor 1 High Temperature Low Temperature High ΔP	3.730	3.799	3.833
	3.533	3.433	3.333
	0.500	0.750	1.500
Reactor 2 High Temperature Low Temperature High ΔP	3.730	3.799	3.833
	3.533	3.433	3.333
	0.500	0.750	1.500

Table 16 - continued

Hydrogen Separator	Caution	Warning	Alarm
Section 1			
High Temperature	2.630	2.730	2.800
Section 2			
High Temperature	2.630	2.730	2.800
High H <sub>2</sub> Outlet Pressure	1.500	2.000	2.500
Recycle Loop			
High Pressure	1.200	1,400	1.500
Low Pressure	0.750	0.500	0.250
Instrumentation			
High Control Temperature	3.540	3.700	3.868

TABLE 17A MONITOR INSTRUMENTATION TRIP POINTS (METRIC UNITS)

Carbon Dioxide Electrolyzer	Caution	Warning	Alarm
Module 1 High Voltage, V Low Voltage, V High Temperature, K Low Temperature, K	3.6	4.0	4.4
	3.0	2.5	2.0
	1133	1143	1148
	1133	1103	1098
Module 2 High Voltage, V Low Voltage, V High Temperature, K Low Temperature, K	3.6	4.0	4.4
	3.0	2.5	2.0
	1133	1143	1148
	1113	1103	1098
Module 3 High Voltage, V Low Voltage, V High Temperature, K Low Temperature, K	3.6	4.0	4.4
	3.0	2.5	2.0
	1133	1143	1148
	1133	1103	1098
High $\Delta P$ , $N/m^2$	1245	1990	2490
Low $\Delta P$ , $N/m^2$	498	473	374
Water Electrolyzer		•	
High Voltage, V Low Voltage, V High Temperature, K Low Temperature, K Low Water Feed Temperature, K	3.6	4.0	4.4
	3.0	2.5	2.0
	1133	1143	1148
	1113	1103	1098
	396	389	383
CO Disproportionator			
Reactor 1 High Temperature, K Low Temperature, K High ΔP, N/m <sup>2</sup>	833	843	848
	803	788	773
	498	747	1475
Reactor 2 High Temperature, K Low Temperature, K High ΔP, N/m	833	843	848
	803	788	773
	498	747	1475

Table 17A - continued

Hydrogen Separator	Caution	Warning	Alarm
Section 1 High Temperature, K	668	683	693
Section 2			
High Temperature, K	668	683	693
High H <sub>2</sub> Outlet Pressure, N/m <sup>2</sup>	2070	2760	3450
Recycle Loop			
High Pressure, N/m <sup>2</sup>	8270	9650	10300
Low Pressure, N/m <sup>2</sup>	5170	3450	1720
Instrumentation			
High Control Temperature, K	325	331	338

TABLE 17B MONITOR INSTRUMENTATION TRIP POINTS (ENGLISH UNITS)

Carbon Dioxide Electrolyzer	Caution	Warning	Alarm
Module 1			
High Voltage, V	3.6	4.0	4.4
Low Voltage, V	3.0	2.5	2.0
High Temperature, F	1580	1598	1607
Low Temperature, F	1544	1526	1517
Module 2			
High Voltage, V	3.6	4.0	4.4
Low Voltage, V	3.0	2.5	2.0
High Temperature, F	1580	1598	1607
Low Temperature, F	1544	1526	1517
Module 3			
High Voltage, V	3.6	4.0	4.4
Low Voltage, V	3.0	2.5	2.0
High Temperature, F	1580	1598	1607
Low Temperature, F	1544	1526	1517
High ΔP, In of Water	5.0	8.0	10.0
Low ΔP, In of Water	2.0	1.9	1.5
Water Electrolyzer			
High Voltage, V	3.6	4.0	4.4
Low Voltage, V	3.0	2.5	2.0
High Temperature, F	1580	1598	1607
Low Temperature, F	1544	1526	1517
Low Water Feed Temperature, F	253	241	230
CO Disproportionator			
Reactor 1			
High_Temperature,_F	1040	1058	1067
Low Temperature, F	986	959	932
High ΔP, In of Water	2.0	3.0	6.0
Reactor 2			
High Temperature, F	1040	1058	1067
Low Temperature, F	986	959	932
High $\Delta P$ , In of Water	2	3	6

Table 17B - continued

Hydrogen Separator	Caution	Warning	Alarm
Section 1 High Temperature, F	743	770	788
Section 2 High Temperature, F High H <sub>2</sub> Outlet Pressure, Psi	743 0.30	770 0.40	788 0.50
Recycle Loop			
High Pressure, Psi Low Pressure, Psi	1.20 0.75	1.40 0.50	1.50 0.25
Instrumentation			
High Control Temperature, F	125.6	136	149

#### CONCLUSIONS AND RECOMMENDATIONS

Based on the results of this program, the following conclusions and recommendations are made:

- 1. A one-man SX-1 is designed, fabricated and assembled. Operation of the following major components was successfully demonstrated.
  - a. CO Disproportionator
  - b. H<sub>2</sub> Separator
  - c. Wäter Feed Mechanism
  - d. Control Instrumentation
  - e. Monitor Instrumentation
- 2. Electrolyzer drum and module technology existing at the inception of the current program was not adequate to produce a leak-free electrolyzer subassembly with 32 electrolyzer drums (64 electrolyzer cells). The design of the electrolyzer modules required 340 high temperature metal-to-metal and metal-to-ceramic seals. Testing performed throughout the program revealed that the reliability of the precious metals/ceramic seals is poor. The erratic occurrence of electrolyzer drum leakage prevented the performance of integrated SX-1 testing.
- 3. It is recommended that further development on the Electrolyzer Cell drum and Electrolyzer Module design be carried out before the solid electrolyte concept for O<sub>2</sub> regeneration is further evaluated. The emphasis on this task would be to minimize the number of high temperature, precious metal/ceramic seals.
- 4. Upon completion of the electrolyzer cell development task described above, it is recommended that the modules required for the one-man system be fabricated, integrated into the SX-1 and SX-1 shakedown, parametric and endurance testing be completed.
- 5. Although the dual reactor concept is an effective means of removing carbon from the system, a continuous carbon removal technique would provide several benefits. It is recommended that a study be conducted aimed at defining a continuous carbon removal technique. This study would involve the identification of alternative techniques for collecting the carbon formed during CO<sub>2</sub> reduction processes. The goal of this study would be to identify possible techniques which would allow the solid carbon to be collected in a continuous manner. Such a technique would enable a decrease in the size of the reactor with a resulting decrease in weight, volume and heat loss and would eliminate the need for frequent cartridge changes, thus reducing the need for expendables. Upon completion of this study, it is recommended that the fabrication and testing of the selected continuous carbon collection technique be completed.

6. The DVT performed on the CO Disproportionator revealed that there was a materials problem in that the electroless nickel failed to prevent carbon formation on designated areas of the CO Disproportionator. It is recommended that a thorough materials evaluation task be performed, with the objective of establishing a material and/or a coating which will prevent carbon formation when exposed to the operating temperature and environment of the CO Disproportionator.

#### REFERENCES

- 1. "Trade-off Study and Conceptual Designs of Regenerative Advanced Integrated Life Support Systems (AILSS)," NASA CR 1458, United Aircraft Corporation, Windsor Locks, CT, January, 1970.
- 2. Nernst, W. Z. Elektrochem., 6, p. 41-43, 1899 to 1900.
- 3. Chandler, Horace W. and Pollara, Frank Z., "Oxygen Regeneration in a Solid Electrolyte System," Chemical Engineering Progress Symposium Series, No. 63, 62, p. 38-42.
- 4. Weissbart, J. and Smart, W. H., "Study of Electrolytic Dissociation of CO<sub>2</sub>-H<sub>2</sub>O Using a Solid Oxide Electrolyte," NASA CR-680, Applied Electrochemistry, Inc., Sunnyvale, CA, February, 1967.
- 5. Weissbart, J. and Smart, W. H., "Development of a CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," NAS2-4843, Applied Electrochemistry, Inc., Sunnyvale, CA, March, 1971.
- 6. Weissbart, J. and Smart, W. H., "CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," Final Report, Contract NAS2-6412, Applied Electrochemistry, Inc., Sunnyvale, CA, January, 1973.
- 7. Weissbart, J., Smart, W. H. and Wydeven, T., "Design and Performance of a Solid Electrolyte Oxygen Generator Test Module," Paper 71 AV-8, SAE/ASME/AIAA Life Support and Environmental Control Conference, San Francisco, CA, July 12-14, 1971.
- 8. Elikan, L. and Morris, J. P., "Solid Electrolyte System for Oxygen Regeneration," NASA CR-1359, Westinghouse Electric Corp., Pittsburgh, PA, June, 1969.
- 9. Elikan, L., Morris, J. P. and Wu, C. K., "Development of a Solid Electrolyte Carbon Dioxide and Water Reduction System for Oxygen," NASA CR-2014. Westinghouse Electric Corp., Pittsburgh, PA, May, 1972.
- 10. Weissbart, J. and Smart, W. H., "Development of a CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," Second Annual Report, Contract NAS2-4843, Applied Electrochemistry, Inc., Mountain View, CA, May, 1970.
- 11. Ring, S. A., Smart, W. H. and Weissbart, J., "CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," First Quarterly Report, Contract NAS2-6412, Applied Electrochemistry, Inc., Sunnyvale, CA, July, 1971.
- 12. Ring, S. A., Smart, W. H. and Weissbart, J., "CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," Second Quarterly Report, Contract NAS2-6412, Applied Electrochemistry, Inc., Sunnyvale, CA, October, 1971.

- 13. Weissbart, J. and Smart, W. H., "CO<sub>2</sub>-H<sub>2</sub>O Solid Oxide Electrolyte Electrolysis System," Third Quarterly Report, Contract NAS2-6412, Applied Electrochemistry, Inc., Sunnyvale, CA, March, 1972.
- 14. Holmes, R. F., Keller, E. E. and King, C. D., "A Carbon Dioxide Reduction Unit using Bosch Reaction and Expendable Catalyst Cartridges," Contract NAS1-8217, Convair Div. of General Dynamics Corp., San Diego, CA, p. 39-40, March, 1970.
- 15. Fabrication of USS Stainless Steels Brochure, ADUSS 03-1478-03, p. 129, February, 1970.
- 16. "Solid Electrolyte Oxygen Regeneration System," Third Quarterly Report, Contract NAS2-7862, ER-190-4-3, p. 3, Life Systems, Inc., Cleveland, OH, July, 1974.
- 17. Smart, W. H. and Weissbart, J., "Solid Electrolyte Oxygen Regenerative System," Applied Electrochemistry, Inc., Sunnyvale, Calif., Subcontract LSI-73-03-01, Prime Contract NAS2-7862, February, 1974.
- 18. Shumar, J., Life Systems, and Holmes, R., General Dynamics, technical discussion.
- 19. Ingelfinger, L., NASA Ames, Wynveen, R. and Shumar, J., Life Systems, technical discussions.
- 20. Smart, W. H. and Weissbart, J., "Solid Electrolyte Oxygen Regeneration System," Quarterly Progress Report No. 1, Applied Electrochemistry, Inc., Sunnyvale, CA, February, 1974.
- 21. "Solid Electrolyte Oxygen Regeneration System," Fourth Quarterly Report, Contract NAS2-7862, ER-190-4-4, Life Systems, Inc., Cleveland, OH, October, 1974.

### APPENDIX 1 SX-1 SEQUENCING FLOW CHART

#### 1.0 SX-1 MAIN FLOW CHART

<u>PURGE Requested?</u> If PURGE has been depressed the answer to this question will be yes and the main program will go to B where B is the PURGE subroutine noted as 2.0. The PURGE subroutine will be carried out and the sequence will return to the main program at point A. If the answer to this question is no, the sequence will drop down to the next decision point.

NORMAL Requested? If NORMAL has been depressed, the answer to this will be yes and flow will drop down to the next decision point. If the answer to this is no, the next decision point will be bypassed.

Previous Mode SHUTDOWN? This decision point asks whether or not the system was previously in a SHUTDOWN mode. If it has been, the answer to this is yes and we go on to the main flow. If the answer is no, we go to C which is the NORMAL subroutine. NORMAL subroutine 3.0 is then carried out and returned to point A. This is in the system to prevent going directly from the SHUTDOWN mode to the NORMAL mode.

REACTOR CHANGE Requested? The REACTOR CHANGE is requested either by the pushbutton or automatically by a signal from the CO disproportionator monitor. If the answer is yes, we go to the next decision point. If the answer is no, we bypass the next decision point.


Previous Mode PURGE, STANDBY, or SHUTDOWN? This decision point is incorporated to prevent going to REACTOR CHANGE mode if the system was previously in PURGE, STANDBY, or SHUTDOWN. If the system was in any of these modes, we would go immediately to the next step, if not, we go to the REACTOR CHANGE subroutine (4.0). After the subroutine is completed, we return to the main flow at point A.


STANDBY Requested? STANDBY is requested either manually by front panel pushbutton or is automatically requested from the monitor. If STANDBY is requested, we go to the next step, if not, we bypass the next step.

Previous Mode PURGE or SHUTDOWN? If the previous mode was PURGE or SHUTDOWN, the STANDBY mode is prohibited and we go to the next step. If not, we go to the STANDBY subroutine (5.0). When this is completed the main program is again put into effect at point A.

SHUTDOWN Requested? If SHUTDOWN is detected either from push-button or system monitor, we go immediately to the SHUTDOWN subroutine (6.0). If not, we cycle back to the start of the main program at point A.

# 1.0 SX-1 MAIN FLOW CHART - continued





## 2.0 PURGE SUBROUTINE

System Reset. All logic is reset and initialized.

Energize PURGE Indicator. The PURGE indicator is energized to notify the operator that the system is in the PURGE mode.

Open SV-112 (Energize). This opens the  $\rm H_2$  separator to vacuum.

Open SV-113 (De-energize). This is open to the  $\rm N_2$  purge and allows RE-101 to control any underpressure situation across the solid oxide electrolyte (SQE) cells.

Open SV-105 (De-energize). This valve is opened to the vacuum which allows RE-102 to control any overpressure condition across the SOE cells.

Open SV-102 (De-energize). This valve opens the purge to the HE-101 water SOE cell.

Open SV-103 (De-energize). This is the main  $N_2$  purge line;  $N_2$  is introduced to recycle loop.

Open SV-109 (De-energize). The opening of this valve allows the  $\rm N_2$  purge to clear the  $\rm H_2$  out of the  $\rm H_2$  separator outlet line.

Energize SV-107 (COD-101 Direction). This action allows the  $\overline{\text{COD-101}}$  to be on line to the N<sub>2</sub> purge.

Open SV-106 (Energize). This valve opens the  $N_2$  purge to clear out the lines to the COD-101.


Start P-101 Motor. The bellows pump will now pump the N<sub>2</sub> purge gases around the recycle loops to clear out all the lines.

Start Timer (Two Minutes). This function starts a two-minute purge cycle time.

<u>Time Out?</u> This decision point allows the  $N_2$  purge to take place for two minutes. If the answer to the question is no, we just sit it in a loop waiting for the timer to time out. When the answer is yes, we fall through to the next process block.

Close SV-102 (Energize). This valve closure shuts off HE-101 to the  $N_2$  purge.

Close SV-103 (Energize). This valve closure stops the main  $N_2$  supply to the recycle loop.



#### 2.0 PURGE SUBROUTINE - continued

Stop P-101 Motor. The recycle loop pump is stopped.


Close SV-106 (De-energize). The  $N_2$  purge supply is cut off to COD-101.

Close SV-109 (Energize). The  $\rm N_2$  purge is shut off to the  $\rm H_2$  separator outlet.

De-energize SV-107. This places the valve in the proper position for COD-101 on-line operation.

Inhibit PURGE Indicator and Reset Purge Flipflop. The PURGE indicator on the front panel is turned off, thus telling the operator the purge cycle has been completed.

Purge complete, return to main program.



## 3.0 NORMAL MODE SUBROUTINE

Energize NORMAL Indicator. The NORMAL indicator on the front panel is energized to notify the operator that the system is now going into the NORMAL model.

Flash NORMAL Indicator. The NORMAL indicator is flashed telling the operator that the system is in a transition state and is heading toward the normal mode of operation.

Inhibit STANDBY and PURGE Indicators and Reset Flops. This is a housekeeping function in order to be sure that only one indicator is on at a time.

Inhibit the STANDBY Elapsed Time Meter. If the system had previously been in the STANDBY mode, the STANDBY time meter would have been stopped at this point.

Enable HE-101 Temperature Control. Power is applied to the HE-101 heater.

Enable CE-101 Temperature Control. Power is applied to the CE-101 heaters.

Enable CE-102 Temperature Control. Power is applied to the CE-102 heaters.

Enable CE-103 Temperature Control. Power is applied to the CE-103 heaters.


Enable HSR-101 and HSR-102 Temperature Controls. Power is applied to the HSR-101 and HSR-102 heaters.

Enable FB-101 Temperature Control. Power is applied to the FB-101 heaters.

Enable P-101 Motor Control. The recycle loop pump is started.

Enable HE-101, CE-101, -102, -103 Current Controls. Current is now supplied to the SOE cells which controls the amount of  $0_2$  that is converted from the feed gas supply.

COD-101 On Line? At this point, one of the CO disproportionators must be on line. To determine which one is on line and if one is on line, the control logic interrogates the four limit switches which are attached to the high temperature valves. These limit switches indicate which COD is on line. If COD-101 is not on line, the program jumps to Step 3.17. If COD-101 is on line, the program goes to Step 3.14.



### 3.0 NORMAL MODE SUBROUTINE - continued

Energize COD-101 On Line Indicator. This indicator is illuminated to notify the system operator that COD-101 is now on line.

Enable COD-101 Temperature Control, Inhibit COD-102

Temperature Control. The COD-101 heaters are now enabled and the COD-102 heaters are disabled. This insures that only the disproportionator that is on line will heat up.

<u>Inhibit COD-102 On Line Indicator</u>. Since the COD-102 is not on line, the indicator is turned off. The sequence goes to Step 3.21 of the flow.

COD-102 On Line? If COD-101 is not on line, this decision point is reached in the program. If the COD-102 is not on line, the loop cycles back and asks if COD-101 is on line. The program sits in this loop until either COD-101 or COD-102 is on line. The normal operation cannot proceed until one of these disproportionators is on line. The operator must place either COD-101 or COD-102 on line for sequence to get out of this loop.

Energize COD-102 On Line Indicator. The COD-102 disproportionator is on line so the indicator is illuminated.

Enable COD-102 Temperature Control, Inhibit COD-101

Temperature Control. The power is applied to the COD-102
heaters and the power is disabled from the COD-101 heaters.

Inhibit COD-101 On Line Indicator. Since COD-101 is no longer on line, the indicator is turned off.

FB-101, COD-101, HSR-101, -102, HE-101, CE-101, -102, -103


At Control Point Temperature? The program sits at this point in the flow until proper operating temperatures have been reached.

Close SV-105 (Energize). At this point in the program, all system components are at their normal operating temperature. SV-105 is closed, isolating the recycle loop from vacuum.

Inhibit Flasher to NORMAL Indicator. The system is now in a normal mode and the NORMAL indicator is held steady.

Enable NORMAL Mode Elapsed Time Meter.

Open SV-101 (Energize). This valve opens the water feed to the flash boiler.




# 3.0 NORMAL MODE SUBROUTINE - continued

 $\underline{\text{Open SV-104 (Energize)}}.$  This valve allows the feed gas into the system.

 $\underline{\text{Close SV-113 (Energize)}}.$  The  $\text{N}_2$  supply is now isolated from the recycle loop.

NORMAL mode in operation, return to main program.



#### 4.0 CARTRIDGE CHANGE MODE SUBROUTINE

Energize REACTOR CHANGE Mode Indicator. This indicator is illuminated, notifying the operator that the system is going towards the REACTOR CHANGE mode.

COD-101 On Line? If COD-101 is not on line, we go to Step 4.32. If COD-101 is on line, then we go the next step.

De-energize SV-107 and SV-110. This configures valve SV-107 and SV-110 such that COD-102 is ready for servicing.

Open SV-111 (Energize). Opening this valve allows COD-102 to be evacuated.

Enable COD-102 Temperature Control. Power is now applied to the COD-102 heaters.

Start Timer (Ten Minutes). A timer is started that will allow COD-102 to be evacuated for a period of ten minutes.

Time Out? The sequence now allows evacuation to take place for ten minutes.

Close SV-111 (De-energize). Evacuation of COD-102 is now complete.

COD-102 At Control Point? The sequence at this point is waiting for the temperature of COD-102 to get to its normal operating point.

Open SV-114 (Energize). Opening this valve allows COD-102 to be filled with feed gas.

Start Timer (Two Minutes). The timer is started for purging COD-102 with fill gas for two minutes.

Time Out? The feed gas is allowed to purge COD-102 for two minutes. The system sits at this point until this occurs.

Close SV-114 (De-energize). Fill gas is now isolated from COD-102. At this point in the sequence, manual intervention is required. The high temperature valves must be configured to place COD-102 on line and COD-101 off line.

Energize OPEN V-2/CLOSE V-1 Indicator. This indicator is illuminated to notify the operator that he should open HV-103 and HV-104 and close HV-102 and HV-101.

Flash Indicator. The indicator is flashed to gain the operator's attention.

4.17 4.18 4.19 4.20 4.23 4.24 4.25 4.28 4.29

4.0 CARTRIDGE CHANGE MODE SUBROUTINE - continued

Cod-102 On Line? If the answer to this is no, the sequence sits in this loop until COD-102 is on line. When this occurs, we go to Step 4.17. This may take some time since the manual operation of opening and closing valves must take place.

Inhibit COD-101 Temperature Control. Since COD-101 is off line, it is now allowed to cool down.

Inhibit OPEN V-2/CLOSE V-1 Indicator. Since COD-102 is now on line, this indicator can be turned off.

Inhibit COD-101 On Line Indicator. Since COD-101 is no longer on line, this indicator is turned off.

Energize COD-102 On Line Indicator. Since COD-102 is now on line, this indicator is illuminated.

COD-101 At Low Temperature? Another manual operation is now necessary. COD-101 is allowed to cool down to its low temperature. When this occurs, we fall through to Step 4.22.

Energize SV-110. This allows COD-101 to be evacuated.

Energize SV-107. This valve allows COD-101 to be serviced.

Open SV-111 (Energize). COD-101 is now open to the vacuum.

Start Timer (Ten Minutes). This timer allows COD-101 to be evacuated for ten minuts.

Time Out? The sequence sits in this loop for ten minutes until COD-101 has been evacuated.

Close SV-111 (De-energize). Evacuation is now complete.

Energize CHANGE CARTRIDGE Indicator. The CHANGE CARTRIDGE indicator is illuminated to notify the operator that he can now remove COD-101.

Flash CHANGE CARTRIDGE Indicator. CHANGE CARTRIDGE indicator is flashed in order to gain the operator's attention. At this time, manual intervention in the automatic sequence is required. The operator must manually open valve V-107 in order to let air into COD-101 chamber. Once this is done, the operator can then pull the cartridge out and replace it with a new one.

CHANGE CARTRIDGE Button Depressed? The sequence rests in this loop until the operator manually depresses the CHANGE CARTRIDGE button. This notifies the sequence that the cartridge change has been completed. The operator must depress this button for normal operation to continue.

4.32 4.33 ₹ 4.34 4.35 4.37 4.40 4.42 4.43 4.44

4.0 CARTRIDGE CHANGE MODE SUBROUTINE - continued

Inhibit CHANGE CARTRIDGE and REACTOR CHANGE Indicators and Reset REACTOR CHANGE Flipflop. The REACTOR CHANGE mode has been completed, therefore, the indicators are turned off.

Change mode complete, return to main program.

Energize SV-107 and SV-110. These valves are put in a position to service COD-101.

Open SV-111 (Energize). COD-101 is now open to vacuum.

Enable COD-101 Temperature Control. Power is applied to the heaters and COD-101 is allowed to heat up during evacuation.

Start Timer (Ten Minutes). A ten-minute timer is started to allow for the evacuation to take place.

Time Out? COD-101 is evacuated for ten minutes. At the end of this time the sequence continues.

Close SV-111, (De-energize). Evacuation has been completed.

COD-101 At Control Point. The sequence sits in this loop waiting for COD-101 to reach its normal operating temperature.

Open SV-114 (Energize). Feed gas is now fed into COD-101.

Start Timer (Two Minutes). The two minute timer is started for purging COD-101 with feed gas.


<u>Time Out?</u> The system sits in this loop for two minutes until the feed gas purge is complete.

Close SV-114 (De-energize). COD-101 has been filled with feed gas and the supply is now shut off.

Energize OPEN V-1/CLOSE V-2 Indicator. This indicator is illuminated in order to tell the operator that he can now place COD-101 on line and take COD-102 off the line.

Flash Indicator. The indicator is flashed to gain the operator's attention.

COD-101 On Line? Sequence sits in this loop waiting for the manual operation to be completed.



# 4.0 CARTRIDGE CHANGE MODE SUBROUTINE - continued

Inhibit COD-102 Temperature Control. Since COD-102 is now off line, power can be removed from its heaters and allowed to cool down.

Inhibit OPEN V-1/CLOSE V-2 Indicator. Since COD-101 is now on line, this indicator can be turned off.


Inhibit COD-102 On Line Indicator. Since COD-102 is no longer on line, this indicator is turned off.

Energize COD-101 On Line Indicator. Since COD-101 is now on line, we illuminate the indicator.

COD-102 At Low Temperature? The system waits in this loop until COD-102 has reached its low temperature.

<u>De-energize SV-107 and SV-110</u>. These valves are placed in a position so that COD-102 can be serviced and made ready for removal.

At this point, the removal sequence is identical to Steps 4.24 through 4.31, thus the program is returned to point H in the program which appears above process block 4.24 in the flow chart.



### 5.0 STANDBY MODE SUBROUTINE

Enable STANDBY Mode Elapsed Time Meter. Since we are starting into the STANDBY mode, we enable the elapsed time meter.

Energize STANDBY Indicator. The STANDBY indicator is illuminated to notify the operator that we are now going into the STANDBY mode.

Open SV-112 (Energize). This places the H<sub>2</sub> separator outlet on line to vacuum.

Increment STANDBY Mode Counter. The STANDBY mode counter is incremented. This keeps track of the number of times the system has gone into the STANDBY mode.

Inhibit SHUTDOWN Indicator. This is a housekeeping function. Shut off the SHUTDOWN indicator in case the system had been in the SHUTDOWN mode prior to coming into the STANDBY mode.

Open SV-105 (De-energize). This allows regulator RE-102 to regulate for overpressure conditions on the SOE cells.

Close SV-102 (Energize). This is a housekeeping chore to prohibit the purge to the HE-101 SOE cell.

Close SV-106 (De-energize). This is a housekeeping chore to prohibit the purge to the CO disproportionators.

Close SV-109 (Energize). This is a housekeeping chore to prohibit purge to the H<sub>2</sub> separator outlet.

Open SV-113 (De-energize). This allows RE-101 to regulate for underpressure conditions with the  $\rm N_2$  supply to the SOE cells.


Close SV-111 (Energize). This is a housekeeping chore in case the system had previously been in a REACTOR CHANGE mode. This prohibits evacuation of the CO disproportionators.

Close SV-101 (De-energize). This shuts off the water supply to the flash boiler.

Close SV-114 (De-energize). This is a housekeeping chore in case the system had been in the REACTOR CHANGE mode. This shuts off the feed gas to the CO disproportionators.

Close SV-103 (Energize). This is a housekeeping chore. It shuts off the  $N_2$  supply to the recycle loop.

continued-



# 5.0 STANDBY MODE SUBROUTINE - continued

Inhibit P-101 Motor Control. The pump is stopped, thus preventing gas flow in the recycle loop.

Close SV-104 (De-energize). The feed gas supply is shut off.

Inhibit NORMAL Mode Elapsed Time Meter. Since we are now in a STANDBY mode, the NORMAL mode elapsed time meter is disabled in case we have come from a NORMAL mode into a STANDBY mode.


Inhibit REACTOR CHANGE Indicator. A housekeeping chore in case we have come from the REACTOR CHANGE mode into the STANDBY mode.

Inhibit NORMAL Indicator. This shuts off NORMAL mode indicator in case we have been in a NORMAL mode prior to entering the STANDBY mode.

Inhibit PURGE Indicator. This turns off the PURGE indicator in case we have been in a PURGE mode prior to STANDBY.

Inhibit HE-101, CE-101, -102, -103 Current Controls. This shuts off the current supply to the SOE cells thus preventing  $\mathbf{0}_2$  generation.

STANDBY or SHUTDOWN in effect, return to main program.



#### 6.0 SHUTDOWN MODE SUBROUTINE

Increment SHUTDOWN Mode Counter and Energize SHUTDOWN Indicator. The SHUTDOWN mode counter is incremented in order to keep track of the number of times the system has been in a SHUTDOWN mode. The SHUTDOWN mode indicator is illuminated to notify the operator that he is now in the SHUTDOWN mode.

Inhibit STANDBY Mode Elapsed Time Meter and STANDBY Indicator.

STANDBY mode elapsed time meter is inhibited in case we had been in the STANDBY mode prior to entering the SHUTDOWN mode. The STANDBY mode indicator is also extinguished at this point.

Inhibit FB-101, HSR-101, HSR-102, COD-101, -102, HE-101, CE-101, -102, -103 Temperature Controls. Power is removed from all the heaters and the system is allowed to cool down.

Close SV-112 (De-energize). The H<sub>2</sub> separator is sealed from vacuum.

At this point in the sequence, the SHUTDOWN mode process steps are identical to the STANDBY Mode process steps, so we return to the STANDBY mode subroutine at point I which is Step 5.6. The sequence continues through Step 5.21 and the system will stabilize in the SHUTDOWN mode. The main program will be entered again at point A and cycling will occur looking for the next request.




FIGURE A1-1 SX-1 SCHEMATIC

		•	